# INSTALLATION INSTRUCTIONS R–410A Variable Speed Split System Air Conditioner CVA9, HVA9, TVA9

#### These instructions must be read and understood completely before attempting installation.

## **TABLE OF CONTENTS**

PAGE	NO.
SAFETY CONSIDERATIONS	
INSTALLATION RECOMMENDATIONS	
INSTALLATION	
STEP 1 — CHECK EQUIPMENT AND JOB SITE 2	
STEP 2 — INSTALL ON A SOLID, LEVEL MOUNTING PAD 2	
STEP 3 — CLEARANCE REQUIREMENTS	
STEP 4 — OPERATING AMBIENT	
STEP 5 — ELEVATE UNIT	
STEP 6 — MAKE PIPING CONNECTIONS	
REFRIGERANT CONNECTIONS AND RECOMMENDED	
LIQUID AND VAPOR TUBE DIAMETERS (IN.)	
STEP 7 — MAKE ELECTRICAL CONNECTIONS 5	
STEP 8 — COMPRESSOR CRANKCASE HEATER 6	
AIRFLOW SETUP FOR OBSERVER FURNACE	
OR FCM4X FAN COIL	
AIRFLOW SETUP FOR NON-COMMUNICATING FAN COIL 6	
AIRFLOW SETUP FOR NON-COMMUNICATING FURNACES 6	
STEP 9 — INSTALL ACCESSORIES	
STEP 10 — START-UP	
STEP 11 — SYSTEM FUNCTIONS AND	
SEQUENCE OF OPERATION	
STEP 12 — CHECK CHARGE	
REQUIRED CHARGE (VALUES IN LBS.)	
ADJUSTMENT FOR INDOOR COIL MODEL	
STEP 13 — PUMPDOWN & EVACUATION	
MAJOR COMPONENTS	
TROUBLESHOOTING	
FACTORY SUPPLIED MODEL PLUG INFORMATION10	
RESISTANCE VALUES VS TEMPERATURE11	
VARIABLE SPEED COMPRESSOR RESISTANCE	
TROUBLESHOOTING	
FINAL CHECKS	
CARE AND MAINTENANCE	
TECHNICAL LABELS	
R-410A QUICK REFERENCE GUIDE	

**IMPORTANT**: Effective January 1, 2015, all split system and packaged air conditioners must be installed pursuant to applicable regional efficiency standards issued by the Department of Energy.

Information in these installation instructions pertains only to CVA9, HVA9, TVA9 series units.

# SAFETY CONSIDERATIONS

Improper installation, adjustment, alteration, service, maintenance, or use can cause explosion, fire, electrical shock, or other conditions which may cause death, personal injury, or property damage. Consult a qualified installer, service agency, or your distributor or branch for information or assistance. The qualified installer or agency must use factory-authorized kits or accessories when modifying this product. Refer to the individual instructions packaged with the kits or accessories when installing.

Follow all safety codes. Wear safety glasses, protective clothing, and work gloves. Use quenching cloth for brazing operations. Have fire extinguisher available. Read these instructions thoroughly and follow all warnings or cautions included in literature and attached to the unit. Consult local building codes and current editions of the National Electrical Code (NEC) NFPA 70. In Canada, refer to current editions of the Canadian electrical code CSA 22.1.

Recognize safety information. This is the safety-alert symbol  $\Delta$ When you see this symbol on the unit and in instructions or manuals, be alert to the potential for personal injury. Understand these signal words; DANGER, WARNING, and CAUTION. These words are used with the safety-alert symbol. DANGER identifies the most serious hazards which **will** result in severe personal injury or death. WARNING signifies hazards which **could** result in personal injury or death. CAUTION is used to identify unsafe practices which **would** result in minor personal injury or product and property damage. NOTE is used to highlight suggestions which **will** result in enhanced installation, reliability, or operation.

# CAUTION

### CUT HAZARD

4

 $\sim$ 

Failure to follow this caution may result in personal injury.

Sheet metal parts may have sharp edges or burrs. Use care and wear appropriate protective clothing and gloves when handling parts.

# WARNING

### UNIT OPERATION AND SAFETY HAZARD

Failure to follow this warning could result in personal injury or equipment damage.

R-410A refrigerant systems operate at higher pressures than standard R-22 systems. Do not use R-22 service equipment or components on R-410A refrigerant equipment.

# WARNING

#### ELECTRICAL SHOCK HAZARD

Failure to follow this warning could result in personal injury or death.

Before installing, modifying, or servicing system, main electrical disconnect switch must be in the OFF position. There may be more than 1 disconnect switch. Lock out and tag switch with a suitable warning label.

**Indoor Thermostat Control Options** 

Model	Observer <sup>®</sup> Wall Control	Standard Thermostat
CVA9, HVA9, TVA9	Yes*	Yes**

NOTE: TSTAT0201CW Communicating Wi-Fi wall control. Non Wi-Fi cannot be used.

All trademarks are the property of their respective owners. Wi-Fi® is a registered trademark of Wi-Fi Alliance Corporation.

\* Version 5.0 software or newer.

\*\* Using standard thermostat limits functionality of system.

# WARNING

#### ELECTRICAL HAZARD - HIGH VOLTAGE!

Failure to follow this warning could result in personal injury or death.

Electrical components may hold charge. DO NOT remove control box cover for 2 minutes after power has been removed from unit.

#### PRIOR TO TOUCHING ELECTRICAL COMPONENTS:

Verify zero (0) voltage at inverter connections shown on inverter cover.

# WARNING

#### EXPLOSION HAZARD



Failure to follow this warning could result in death, serious personal injury, and/or property damage.

Never use air or gases containing oxygen for leak testing or operating refrigerant compressors. Pressurized mixtures of air or gases containing oxygen can lead to an explosion.

### **Inverter** Cover

**IMPORTANT:** The inverter cover should NEVER be removed because there is no reason to remove the inverter cover to access the inverter. The inverter has limited serviceability. Refer to Service Manual for details on field replaceable parts. A replacement cover is provided with a replacement inverter.

# INSTALLATION RECOMMENDATIONS

In some cases noise in the living area has been traced to gas pulsations from improper installation of equipment.


- 1. Locate unit away from windows, patios, decks, etc. where unit operation sound may disturb customer.
- 2. In noise sensitive applications (such as bedrooms), when a lineset is mounted to ceiling joists or floor joists, the outdoor unit must be located at least 10 ft (3.05 m) away. If this is not possible, create a line set configuration with enough bends to provide 10 ft (3.05 m) of total line set length outside the dwelling
- 3. Ensure that vapor and liquid tube diameters are appropriate for unit capacity.
- Run refrigerant tubes as directly as possible by avoiding unnecessary turns and bends.
- 5. Leave some slack between structure and unit to absorb vibration.
- When passing refrigerant tubes through the wall, seal opening with RTV or other pliable silicon-based caulk (see Fig. 1).
- 7. Avoid direct tubing contact with water pipes, duct work, floor joists, wall studs, floors, and walls.
- 8. Do not suspend refrigerant tubing from joists and studs with a rigid wire or strap which comes in direct contact with tubing (see Fig. 1).
- 9. Ensure that tubing insulation is pliable and completely surrounds vapor tube.
- 10. When necessary, use hanger straps which are 1 in. wide and conform to shape of tubing insulation. (See Fig. 1.)
- 11. Isolate hanger straps from insulation by using metal sleeves bent to conform to shape of insulation.

# **A** CAUTION

#### EQUIPMENT DAMAGE HAZARD

Failure to follow this caution may result in equipment damage.

If proper lineset routing techniques are not followed, variable speed systems can be susceptible to lineset transmitted noise inside the dwelling and, in extreme cases, tubing breakage.



A07588

Fig. 1 – Connecting Tubing Installation

The outdoor unit contains the correct amount of refrigerant charge for operation with AHRI rated indoor units when connected by 15 ft (4.57 m) of field–supplied or factory accessory tubing.

See Step 12 on page 7 for proper charging procedure.

**IMPORTANT:** Liquid–line size is 3/8–in. OD for all CVA9, HVA9, TVA9 applications. The maximum allowable equivalent line set length is 100 ft. (30.5 m).

**IMPORTANT:** Always install the factory–supplied liquid–line filter drier. Obtain replacement filter driers from your distributor or branch.

# INSTALLATION

Specifications for this unit in residential new construction market require the outdoor unit, indoor unit (including metering device), refrigerant tubing sets, and filter drier listed in pre-sale literature. There can be no deviation. Consult the Service Manual – Air Conditioners and Heat Pumps Using R-410A Refrigerant to obtain required unit changes for specific applications and for R-22 retrofit.

# Step 1 — Check Equipment and Job Site

#### <u>Unpack Unit</u>

Move to final location. Remove carton taking care not to damage unit.

#### **Inspect Equipment**

File claim with shipping company prior to installation if shipment is damaged or incomplete. Locate unit rating plate on unit corner panel. It contains information needed to properly install unit. Check rating plate to be sure unit matches job specifications.

### Step 2 — Install on a Solid, Level Mounting Pad

If conditions or local codes require the unit be attached to pad, tie down bolts should be used and fastened through knockouts provided in unit base pan. Refer to unit mounting pattern in Fig. 2 to determine base pan size and knockout hole location.

For hurricane tie downs, contact distributor for details and PE (Professional Engineer) Certification, if required.

On rooftop applications, mount on level platform or frame. Place unit above a load-bearing wall and isolate unit and tubing set from structure. Arrange supporting members to adequately support unit and minimize transmission of vibration to building. Consult local codes governing rooftop applications.


Roof mounted units exposed to winds above 5 mph may require wind baffles. Consult the Service Manual – Residential Split System Air Conditioners and Heat Pumps Using R-410A Refrigerant for wind baffle construction.

**NOTE:** Unit must be level to within  $\pm 2^{\circ}$  ( $\pm 3/8$  in./ft, $\pm 9.5$  mm/m.) per compressor manufacturer specifications.

#### Step 3 — Clearance Requirements

When installing, allow sufficient space for airflow clearance, wiring, refrigerant piping, and service. Allow 24 in. (609.6 mm) clearance to service end of unit and 48 in. (1219.2 mm) (above unit. For proper airflow, a 6–in. (152.4 mm) clearance on 1 side of unit and 12–in. (304.8 mm) on all remaining sides must be maintained. Maintain a distance of 24 in. (609.6 mm) between units. Position so water, snow, or ice from roof or eaves cannot fall directly on unit.

On rooftop applications, locate unit at least 6 in. (152.4 mm) above roof surface.





UNIT BASE PAN	TIEDOWN KNOCKOUT LOCATIONS in. (mm)					
Dimension in. (mm)	Α	A B C				
23 X 23 (596 X 596)	7—13/16 (198)	4-7/16 (102)	18-1/8 (458)			
31.2 X 31.2 (792 X 792)	9-1/8 (232)	6—9/16 (167)	24—11/16 (627)			
35 X 35 (889 X 889)	9-1/8 (232)	6-9/16 (167)	28-7/16 (722)			

Fig. 2 – Tie-down Knockout Locations

#### Step 4 — Operating Ambient

The minimum outdoor operating ambient is  $40^{\circ}$ F (4.4°C) with Observer<sup>®</sup> Wall Control, 55°F (12.8°C) with non-communicating systems. The maximum outdoor operating ambient is 115°F (46.1°C). Compressor protections will prevent operation below minimum ambient temperature range. The system may operate in cooling up to 125°F (52°C) (52C) with significant reduced capacity cutback above 115°F (46.1°C). Refer to Product Data "Detailed Cooling Capacity" table. Low ambient cooling operation is not currently available.

#### Step 5 — Elevate Unit

Elevate unit per local climate and code requirements to provide clearance above estimated snowfall level and ensure adequate drainage of unit.

# **A** CAUTION

#### UNIT OPERATION HAZARD

Failure to follow this caution may result in equipment damage or improper operation.

Do not allow water and/or ice to build up in base pan.

# CAUTION

#### UNIT OPERATION HAZARD

A

Ŷ

Failure to follow this caution may result in equipment damage or improper operation.

Locate the unit in such a way that it is stable in all circumstances including adverse weather conditions.

## Step 6 — Make Piping Connections



# PERSONAL INJURY AND UNIT DAMAGE HAZARD

Failure to follow this warning could result in personal injury or death.

Relieve pressure and recover all refrigerant before system repair or final unit disposal. Use all service ports and open all flow-control devices, including solenoid valves.

# CAUTION

#### UNIT DAMAGE HAZARD

Ą

Failure to follow this caution may result in equipment damage or improper operation.

Do not leave system open to atmosphere any longer than minimum required for installation. POE oil in compressor is extremely susceptible to moisture absorption. Always keep ends of tubing sealed during installation.



#### UNIT DAMAGE HAZARD

Failure to follow this caution may result in equipment damage or improper operation.

If ANY refrigerant tubing is buried, provide a 6 in. (152.4 mm) vertical rise at service valve. Refrigerant tubing lengths up to 36 in. (914.4 mm) may be buried without further special consideration. Do not bury lines longer than 36 in. (914.4 mm).

Outdoor units may be connected to indoor section using accessory tubing package or field-supplied refrigerant grade tubing of correct size and condition. For tubing requirements between 80 - 100 ft. (24.38 - 30.48 m), capacity and performance losses can occur. Follow the pipe sizing recommendations in the CVA9, HVA9, TVA9 Product data to manage these losses. This unit shall not be installed with greater than 100 ft (30.48 m) of equivalent line length.

Refer to Table 1 for field tubing diameters. No additional accessories are required for line lengths between 80 - 100 ft. (24.4 - 30.5 m) on this product.

Table 1 - Refrigerant Connections and Recommended Liquid and	d Vapor Tube Diameters (in.)
--	------------------------------

	LIQUID			VAPOR <sup>†</sup>	
CVA9, HVA9, TVA9	Connection Diame-	Tube Diameter	Connection Di-	Max (Rated) Diam-	Minimum Tube Diame-
	ter	Tube Diameter	ameter	eter	ter
24	3/8	3/8	3/4	3/4	5/8
25	3/8	3/8	3/4	7/8	5/8
36, 37	3/8	3/8	3/4	7/8	5/8
48, 49	3/8	3/8	7/8	(1-1/8)	3/4
60	3/8	3/8	7/8	(1-1/8)	3/4

† Units are rated with 25 ft. (7.6 m) of lineset. See Product Data sheet for performance data when using different size and length line sets.

Notes:

1. Do not apply capillary tube indoor coils to these units.

#### **Outdoor Unit Connected to Factory-Approved Indoor** Unit

Outdoor unit contains correct system refrigerant charge for operation with factory-approved, AHRI-rated indoor units when connected by 15 ft. (4.57 m) of field-supplied or factory-accessory tubing, and factory-supplied filter drier. Check refrigerant charge for maximum efficiency.

NOTE: If the indoor furnace coil width is more than the furnace casing width, refer to the indoor coil Installation Instructions for transition requirements.

### Install Liquid-Line Filter Drier Indoor

Refer to Fig. 3 and install filter drier as follows:

- 1. Braze 5-in. (127 mm) liquid tube to the indoor coil.
- 2. Wrap filter drier with damp cloth.
- 3. Braze filter drier to above 5-in. (127 mm) liquid tube.
- 4. Connect and braze liquid refrigerant tube to the filter drier.

# CAUTION

#### UNIT DAMAGE HAZARD

 $\Lambda$ 

Failure to follow this caution may result in unit damage or improper operation.

Installation of filter drier in liquid line is required.




Fig. 3 - Liquid-Line Filter Drier

#### **Refrigerant Tubing connection Outdoor**

Connect vapor tube to fitting on outdoor unit vapor service valves (see Table 1).

## **Sweat Connections**

# **CAUTION**

#### UNIT DAMAGE HAZARD

 $\Lambda$ 

Failure to follow this caution may result in equipment damage or improper operation.

- Use a brazing shield
- Wrap service valves with wet cloth or heat sink material.

Use refrigerant grade tubing. Service valves are closed from factory and ready for brazing. After wrapping service valve with a wet cloth, braze sweat connections using industry accepted methods and materials. Consult local code requirements. Refrigerant tubing and indoor coil are now ready for leak testing. This check should include all field and factory joints.

#### **Evacuate Refrigerant Tubing and Indoor Coil**



#### UNIT DAMAGE HAZARD

Failure to follow this caution may result in equipment damage or improper operation.

Never use the system compressor as a vacuum pump.

Refrigerant tubes and indoor coil should be evacuated using the recommended deep vacuum method of 500 microns. The alternate triple evacuation method may be used. See Service Manual for triple evacuation method. Always break a vacuum with dry nitrogen prior to opening the refrigerant system for servicing.

#### **Deep Vacuum Method**

The deep vacuum method requires a vacuum pump capable of pulling a vacuum of 500 microns and a vacuum gauge capable of accurately measuring this vacuum depth. The deep vacuum method is the most positive way of assuring a system is free of air and liquid water. (See Fig. 4)




Fig. 4 - Deep Vacuum Graph

### **Final Tubing Check**

Ą

**IMPORTANT:** Check to be certain factory tubing on both indoor and outdoor unit has not shifted during shipment. Ensure tubes are not rubbing against each other or any sheet metal. Pay close attention to feeder tubes, making sure wire ties on feeder tubes are secure and tight.

#### Step 7 — Make Electrical Connections



#### ELECTRICAL SHOCK HAZARD

Failure to follow this warning could result in personal injury or death.

Do not supply power to unit with compressor terminal box cover removed.

Be sure field wiring complies with local and national fire, safety, and electrical codes, and voltage to system is within limits shown on unit rating plate. Contact local power company for correction of improper voltage. See unit rating plate for recommended circuit protection device.

**NOTE:** Operation of unit on improper line voltage constitutes abuse and could affect unit reliability. See unit rating plate. Do not install unit in system where voltage may fluctuate above or below permissible limits.

**NOTE:** Use copper wire only between disconnect switch and unit. **NOTE:** Install branch circuit disconnect of adequate size per NEC to handle unit starting current. Locate disconnect within sight from and readily accessible from unit, per Section 440–14 of NEC.

#### **Route Ground and Power Wires**

Remove access panel to gain access to unit wiring. Extend wires from disconnect through power wiring hole provided and into unit control box.

# WARNING

#### ELECTRICAL SHOCK HAZARD


Ą


Failure to follow this warning could result in personal injury or death.

The unit cabinet must have an uninterrupted or unbroken ground to minimize personal injury if an electrical fault should occur. The ground may consist of electrical wire or metal conduit when installed in accordance with existing electrical codes.

### **Connect Ground and Power Wires**

Connect ground wire to ground connection in control box for safety. Connect power wiring to contactor as shown in Fig. 5.







#### Observer<sup>®</sup> Control Wiring – Observer Wall

Connect four wires from Observer to communicating furnace / fan coil with communicating motor capability. Only two wires from furnace / fan coil DX+ (GR), DX- (YL) are connected to the outside inverter wiring GR (DX+), YL (DX-) (see Fig. 6). Connect C (WT) is recommended if wires are available (see Fig. 6). This will reduce the chance of communication issues. Unused low voltage wires should be bundled together and terminated with a wire nut at each end. The end nearest indoor coil should be connected to C terminal.

**IMPORTANT**: This system requires the power supplied to the outdoor unit, and the indoor unit, for the Observer Wall Control to communicate with the outdoor unit.





#### Connect Control Wiring- Non-Communicating

4 wires are required when connecting CVA9, HVA9, TVA9 models to non-communicating 2-stage thermostats. Use Fig. 7 For required connections. Unit is configured by factory for Observer<sup>®</sup> communicating control. To wire unit for non-communicating control, disconnect the DX+ = GN and DX- = YL wires from green plug and connect appropriate wires to low voltage terminal block. Use wire nuts to attach thermostat wire to low voltage choke harness LVCH harness.

#### **General Information**

Use 18–20 solid AWG color–coded, insulated (355C minimum) wire for low voltage control wires. All wiring must be NEC Class 2 and must be separated from incoming power leads.


Installations using greater than 200 feet of low voltage wiring should consult the Observer wall control manual for additional guidelines regarding daisy chaining wiring method and terminating resistors.

Never route control wiring in parallel to high voltage power wires when possible as electrical noise may transfer and generate nuisance fault codes. Where low voltage control and high voltage wires must cross paths, do so at perpendicular angles to eliminate transferred noise. If further communication issues exist, consider using shielded low voltage wires and only connect shielding to C terminal at end nearest indoor coil.


Use furnace transformer, fan coil transformer, or accessory transformer for control power requirement of system accessories external to the OD unit. The outdoor unit has its own transformer power.

### **Final Wiring Check**


**IMPORTANT:** Check factory wiring and field wire connections to ensure terminations are secured properly. Check wire routing to ensure wires are not in contact with tubing, sheet metal, etc. Ensure that high and low voltage is separated where possible, to minimize induced noise from VFD to communication wiring.



A150213



A150214



#### This compressor has an internal crankcase heater. Furnish power to the unit a minimum of 24 hours before starting the unit for the first time.

Upon initial start-up of unit, status code 68 will be generated and system will operate at stage 2 for 11 minutes. This operation is important to system reliability and cannot be bypassed. Each time high voltage is removed and reapplied this behavior will be repeated.

To furnish power to heater only, set thermostat to OFF and close electrical disconnect to outdoor unit.

Power is not required to the indoor unit or Observer<sup>®</sup> Wall Control for proper operation of heater. Crankcase heater will be intelligently energized as needed between operations, even when the Observer Wall Control or thermostat and indoor unit is not installed, as long as there is power to the outdoor unit.

# Airflow Setup for Observer Furnace or FCM4X Fan Coil (communicating)

This system can only be installed with communicating indoor and Observer Wall Control TSTAT0201CW software version 5.0 or greater. When using a Observer Wall Control, airflow is automatically selected based on equipment size. The user has the option of selecting Comfort, Efficiency and Max airflow for Cooling modes. These should be selected based on balance between the homeowner's comfort and energy consumption expectations. See Observer Wall Control Installation Instructions for additional available adjustments.

Due to using a communicating control with the fan coil or the furnace, dip switch adjustments are not necessary. The outdoor unit configuration and the indoor airflows are determined by communicating control setup.

## Airflow Setup for Non-communicating Fan Coil


The system can be installed with a standard 2–stage thermostat and FVM4X fan coil without additional accessories. Select appropriate unit size on fan coil Easy select board.

## Airflow Setup for Non-communicating Furnaces

For installations with non-communicating furnaces, set airflows to 350–400 cfm/nominal ton in high stage and 70–80 percent of high stage airflow in low stage.

# Step 9 — Install Accessories

No refrigeration circuit accessories are required or are available for installation within the unit. External to the unit, the same accessories such as support feet, wind baffle etc., available on other units, can also be used on this line of product. For models utilizing 23 inch x 23 inch base pans, it is recommended to use 5 support feet in order to fully support unit. See Fig. 8. Refer to the individual Installation Instructions packaged with kits or accessories when installing.



A14008

Fig. 8 – Recommended Support Feet Location (for 23 x 23 basepans)

#### Step 10 — Start-Up

Ŋ



#### UNIT OPERATION AND SAFETY HAZARD

Failure to follow this caution may result in minor personal injury, equipment damage or improper operation.

Observe the following:

- 1.Do not overcharge system with refrigerant.
- 2.Do not operate unit in a vacuum or at negative pressure.
- 3.Do not disable low pressure transducer or system safety devices such as discharge thermistor or the high pressure switch.
- 4.Dome temperatures may be hot.
- 5.Discharge thermistor is engaged tight on the discharge tube.

# CAUTION

### PERSONAL INJURY HAZARD

Failure to follow this caution may result in personal injury.

Wear safety glasses, protective clothing, and gloves when handling refrigerant.

# CAUTION

### ENVIRONMENTAL HAZARD

Failure to follow this caution may result in environmental damage.

Federal regulations require that you do not vent refrigerant to the atmosphere. Recover during system repair or final unit disposal.

# Step 11 — System Functions and Sequence of Operation

The CVA9, HVA9, TVA9 models utilize either Observer<sup>®</sup> Wall Communicating Wall Control or conventional thermostat. When using Wall Control controls, a call for cooling will energize the outdoor fan and compressor to run at lowest cooling demand. If this does not satisfy cooling demand, the system will ramp up in stages until it satisfies the demand. After coping with the higher demand, the unit returns to lower capacity operation until the demand is satisfied or until an increase in demand. When using a conventional thermostat, the thermostat controls the staging of outdoor unit.

When all demand is satisfied, the compressor will shut off. As the unit operates at lower capacity, system vapor (suction) pressure will be higher than it is during a standard single–stage system operation or during a higher capacity operation.

The Observer Wall Control displays the operation mode and fault codes as specified in the troubleshooting section. See Table 6 for codes and definitions.

The conventional thermostat inputs are designed to work with most indoor units. See AHRI for approved combinations. Connections are Y/Y2, Y1, R and C. Depending on thermostat and indoor unit, the system will operate at 1 or 2 capacities in cooling mode.

**NOTE:** Only one code will be displayed on the outdoor unit control board (the most recent, with the highest priority). The latest codes are stored and can be accessed via the Observer Wall Control.

Upon a call for cooling through the Observer Wall Control (or the Y1 and/or Y2 connections in a non-communicating system), the Application Operation Control (AOC) board (see Fig. 17) will request a compressor speed and outdoor fan motor speed based on the indoor space demand and outdoor conditions.

If the conditions are correct for operation, the control board will allow the requested operation to begin, but if the control board determines that the conditions are not correct, the board will decide what other operation nearing that condition is acceptable. The inverter Motor Operational Control (MOC) then outputs the three–phase PWM signal and frequency that gently ramps the compressor speed up to stage 2, and then will adjust to the demanded speed. The gentle ramp–up results in no locked rotor amps to the compressor motor. The unit nameplate for compressor LRA will be stamped N/A (not applicable).


During operation, the AOC monitors itself and the compressor operation along with the system pressures and temperatures. The MOC board monitors the temperature, current and operational status of the compressor, OD fan and the inverter itself. During operation, the compressor speed will be adjusted to meet the changes to the demand.

### **Outdoor Fan Motor Operation**

The compact ECM outdoor fan motor is a variable–speed brushless DC (BLDC) motor that operates at speeds from 400 to 1050 RPM. The motor is a 3–phase permanent magnet–type motor. Just like the compressor, this motor speed is determined by the inverter output frequency and amplitude. (Fig. 9)

Motor speed is controlled through the inverter board in the outdoor unit and no electronic module is attached. Motor speed is slowed as the building load decreases, maintaining the proper condensing temperature for both cooling and dehumidification. As the building load increases, the motor will increase speed until it is at maximum speed at the maximum building load.

At unit start-up, there is a slight delay and thrust motion of the fan motor/blade in the reverse direction, prior to ramping-up the fan assembly.



#### Fig. 9 – AOC Control Board

### Step 12 — Check Charge

**Charging Procedure:** Force system to operate in high stage cooling by creating a large differential between room temperature and set point on thermostat. If using conventional 2–stage thermostat, use multi-meter to verify that 24 VAC is present between C, Y1 /Y2 terminals at outdoor unit.

Factory charge amount is shown on unit rating plate for high stage. Target subcooling chart is provided on back of control box door see Fig. 10 – 16 for example. To properly check or adjust charge, condition must be favorable for subcooling charging. Favorable conditions exists when outdoor temperature is between  $65^{\circ}$ F ( $18^{\circ}$ C) and  $100^{\circ}$ F ( $38^{\circ}$ C), and the indoor temperature is between  $70^{\circ}$ F ( $21^{\circ}$ C) and  $80^{\circ}$ F ( $27^{\circ}$ C). Follow the procedure below:

Unit is factory charged for 15ft (4.57 m) of lineset. Adjust charge by adding or removing 0.6 oz/ft (17.7 g/m) of 3/8 liquid line above or below 15ft (4.57 m) respectively.

For standard refrigerant line lengths (80ft/24.4 m or less), allow system to operate in cooling mode at least 25 minutes. If conditions are favorable, check system charge by subcooling method. If any adjustment is necessary, adjust charge slowly and allow system to operate for 25 minutes to stabilize before declaring a properly charged system.

If the indoor temperature is below 70°F (21.11°C), or the outdoor temperature is not in the favorable range, adjust charge for line set length above or below 15ft (4.57 m) and indoor fan coil /furnace coil per Table 4. Charge level should then be appropriate for the system to achieve rated capacity. The charge level should then be checked at another time when the both indoor and outdoor temperatures are in a more favorable range.

NOTE: If the line length is beyond 80ft (24.38 m) or greater than 20ft (6.10 m) vertical separation see Long line guideline for special charging requirement.

# Table 2 – Required Charge (values in lbs.)Adjustment for Indoor Coil Model

Furnace Coil or Fan Coil Model	24	25	36	37	48	49	60
EA*4X24	-	-	/	/	/	/	/
EHD4X24	-	-	/	/	/	/	/
EHD4X30	-	-	/	/	/	/	/
F(V,C)M4X24	/	-	-	/	/	/	/
EA*4X30	-	-	/	/	/	/	/
EN(A,D)4X30	-	-	/	/	/	/	/
ENH4X36	-	-	-	-	/	/	/
F(V,C)M4X36	/	-	-	-	/	/	/
EA*4X36	-	+.50	-	-	/	/	/
END4X42	+.50	+.50	-	+.75	/	/	/
EA*4X42	+.50	+.50	-	+.75	/	/	/
EHD4X36	+.50	+.50	-	+.75	/	/	/
EHD4X42	+.50	+.50	+.75	+.75	/	/	/
EN(A,D)4X31	+.50	+1.25	+.75	+.75	/	/	/
EN*4X48	+.50	+1.25	+.75	+.75	-	-	/
EHD4X48	+.63	+1.25	+.75	+1.00	-	-	/
EN(A,D)4X37	+.63	+1.25	+.75	+1.00	-	-	/
EN(A,D)4X43	+.63	+1.25	+.75	+1.00	-	-	/
EA*4X48	/	/	+.75	+1.00	-	-	/
EN*4X60	/	/	/	+1.00	-	+.13	-
EHD4X60	/	/	/	+1.00	-	+.13	-
F(V,C)M4X48	.63	+1.25	+.75	+1.00	-	+.13	/
F(V,C)M4X60	/	/	+.75	+1.00	+1.50	+.63	+1.00
EA*4X60	/	/	/	/	+1.50	+.63	+1.00
EN*4X61	/	/	/	/	+1.50	+.63	+1.00

/ = Comb. not allowed

– = No charge adjust for ID
 Note: Charge adders are in decimal format




Fig. 10 - Charging in Cooling Mode CVA9, HVA9, TVA924








Fig. 11 – Charging in Cooling Mode CVA9, HVA9, TVA925





















Fig. 16 - Charging in Cooling Mode CVA9, HVA9, TVA960

### Step 13 — Pumpdown & Evacuation

# CAUTION

#### ENVIRONMENTAL HAZARD

Failure to follow this caution may result in environmental damage.

Federal regulations require that you do not vent refrigerant to the atmosphere. Recover during system repair or final unit disposal.

If this system requires either a Pump Down or Evacuation for any reason, the procedures below must be followed:

#### Pump Down

Because this system has an inverter controlled compressor, suction pressure transducer, conventional procedure cannot be used to "pump down" and isolate the refrigerant into the outdoor unit.

- 1. Connect gauges to CVA9, HVA9, TVA9 liquid and vapor service valve ports to monitor operating pressures during and at completion of the procedure.
- 2. Force system to operate in high stage by creating a large differential between room temperature and set point on thermostat. Use multi-meter to verify that 24 VAC is present between C and Y1 and Y2 terminals at outdoor unit.
- 3. Close the liquid service valve.
- 4. The unit will continue to run until high or low pressure switches open. Close vapor service valve once compressor shuts down.
- 5. Remove power from indoor and outdoor unit prior to servicing unit.
- 6. A quantity of charge will remain in isolated section of system dependent on ambient temperature and overall system charge. This charge must be manually recovered. A recovery system will be required to remove final quantity of refrigerant from indoor coil and line set.

#### Evacuation and recovery of refrigerant from CVA9, HVA9, TVA9

- 1. Connect gauges to CVA9, HVA9, TVA9 liquid and vapor service valve ports to monitor operating pressures during and at completion of the procedure. Attach recovery system or vacuum pump to gauge set as needed for the service procedure. The service valves must be open to evacuate the unit through the line set service ports.
- 2. Begin evacuation or refrigerant. Allow extra time for refrigerant recovery and establishing a thorough evacuation.

# MAJOR COMPONENTS

Variable Speed Control Board



A13361

#### Fig. 17 – AOC (Application Operational Control) Board

The AOC board is located in the lower right hand side of inverter tray. It's functions include:

- Compressor speed control
- Outdoor fan motor control
- Crankcase heater operation
- Pressure switch monitoring
- Time Delays
- Pressure Transducer measurements
- PEV control (pressure equalizer valve)
- Temperature measurements
- Inverter communication and control

#### <u>Inverter</u>

The inverter is located inside the control box. This is an air–cooled device that communicates with the control board and drives the compressor and fan motor to the demanded RPM. The inverter is always powered with line voltage since no contactor is used. The inverter changes the line voltage to DC volts and then recreates 3 phase sine waves that vary in frequency to drive the compressor and fan motor at the desired RPM.

NOTE: The unit may be operated with an Observer<sup>®</sup> Wall Control or a standard 2–stage thermostat. Observer Wall Control will utilize 5 stages cooling, while 2–stage thermostat will only allow 2 discrete stages of cooling operation.

#### Variable Speed Compressor

This unit contains a variable speed rotary compressor that has a wide operating range. It operates on a variable 3 phase sine wave provided by the inverter. This compressor can only be operated by the specific inverter supplied with the unit.

# **A** CAUTION

#### EQUIPMENT DAMAGE HAZARD

Failure to follow this caution may result in equipment damage and/or improper operation.

Do not attempt to apply line voltage directly to the compressor. This will destroy the compressor.

#### **Field control Connections**

For communicating operation use the communication Observer<sup>®</sup> plug only. Only two wires, DX+, DX– (GN,YL), are required. If necessary, connect C for additional grounding (see Fig. 6). If using standard 2–stage thermostat, connect discrete inputs (R,C,Y2,Y1) for 2–stage control in cooling modes.

#### Pressure Transducer (SPT)

A 5 VDC output low pressure transducer that provides a 0-5 VDC data for interpretation by the control board for a 0 to 200 psig range of pressure at the suction tube. This interpreted pressure data is then intelligently used by the AOC control board for low pressure cut–out, loss of charge management, compressor protection, oil circulation management, and lubrication management.

#### **Pressure Equalizer Valve (PEV)**

At the end of every compressor operation (after the 3.5 minute Time Guard period), the equalizer valve opens for 150 seconds plus an additional 15 seconds of protection before allowing the compressor to start ramping up.

The PEV is located next to the suction and discharge of the compressor. The function of this valve is to prevent the compressor from starting with a high refrigerant pressure differential, thus helping the reliability of the compressor.

NOTE: A hissing sound may be heard during the equalization process. This is normal.

### TROUBLESHOOTING

#### **Systems Communication Failure**

If communication is lost with the Observer Wall Control, the control will flash the appropriate fault code (see Table 6). Check the wiring to the Observer Wall Control and the indoor and outdoor units and power.

#### Model Plug

Each control board contains a model plug. The correct model plug must be installed for the system to operate properly (see Table 3).

The model plug is used to identify the type and size of unit to the control.

On new units, the model and serial numbers are inputted into the AOC board's memory at the factory. If a model plug is lost or missing at initial installation, the unit will operate according to the information input at the factory and the appropriate error code will flash temporarily. A FAST Parts replacement AOC board contains no model and serial information. If the factory control board fails, the model plug must be transferred from the original board to the replacement board for the unit to operate.

When installing AC unit with older fan coils, a model plug change may be required.

NOTE: The model plug takes priority over factory model information input at the factory. If the model plug is removed after initial power up, the unit will operate according to the last valid model plug installed, and flash the appropriate fault code temporarily.

#### Table 3 – Factory Supplied Model Plug Information

CVA9, HVA9,	MODEL PLUG	PIN RESISTANCE (K-OHMS)	
TVA9	NUMBER	1-4 (R1)	2-3 (R2)
24	HK70EZ041	18K	91K
25	HK70EZ032	18K	5.1K
36	HK70EZ043	18K	150K
37	HK70EZ034	18K	18K
48	HK70EZ045	18K	220K
49	HK70EZ036	18K	33K
60	HK70EZ047	18K	360K

#### **Pressure Switch Protection**

The outdoor unit is equipped with high pressure switch. If the control senses the opening of a high pressure switch (open 600+/-5 psig, close 470+/-10 psig  $@77^{\circ}F$ ), it will respond as follows:

- 1. Display the appropriate fault code (see Table 6).
- 2. After a 6 minute delay, if there is a call for cooling and HPS is reset, the PEV opens for 150 seconds to equalize system pressures. The compressor and fan will then ramp to the next lower stage of operation until demand is satisfied. The staging down and resetting to the highest stage will end after 2 hours of accumulated operation without further HPS trips.
- 3. A system malfunction will occur after repeated HPS faults and the stages has reached the lowest level. This could take five consecutive HPS trips if the first occurred in stage 5 demand or 1 HPS trip if in stage 1 demand.
- 4. In the event of a high–pressure switch trip or high–pressure lockout, check the refrigerant charge, outdoor fan operation, and outdoor coil (in cooling) for airflow restrictions.
- 5. In the event of a low-pressure trip or low-pressure lockout, check the refrigerant charge and indoor airflow (cooling).

#### **Control Fault**

If the outdoor unit control board has failed, the control will flash the appropriate fault code (see Table 6). The control board should be replaced.

#### **Brown-Out Protection**

If the line voltage is less than 187V for at least 4 seconds, the Compressor and OD fan goes to 0 rpm. Compressor and fan operation are not allowed until voltage is a minimum of 190V. The control will flash the appropriate fault code (see Table 6).

#### 230V Line (Power Disconnect) Detection

The control board senses the presence of absence of 230V through inverter feedback. Voltage should present at all times when system is in service regardless if system is running or standby. If there is no 230V at the inverter when the indoor unit is powered with a cooling demand, the appropriate fault code is displayed on Wall Control (communicating only – see Table 6). If system is configured with conventional thermostat (non–communicating), no fault code will be displayed on AOC board, nor will any status LEDs be lit. Use multimeter to check for the presence of 230V in this situation.

#### **Temperature Thermistors**

Thermistors are electronic devices which sense temperature. As the temperature increases, the resistance decreases. 10Kohm thermistors are used to sense outdoor air temperature (OAT), coil temperature (OCT) and the suction line temperature (OST) located between the reversing valve and the accumulator. A 50Kohm thermistor is used to sense discharge temperature (ODT).

Refer to Table 4 and Fig. 18 and 19 for resistance values versus temperature.

Table 4 – 10K/50Kohm Resistance Values vs Temperature

10Kohms °C (°F)					
TEMPERATURE	RESISTANCE (Kohms)				
25.0 (77.0)	10.0 + / - 2.3%				
0.0 (32.0)	32.6 + / - 3.2%				
-28.0 (-18.4)	85.5 + / - 3.4%				
50	Kohms				
125.0 (257.0)	1.7 + / - 1.6%				
75.0 (167.0)	7.40 + / - 2.0%				
25.0 (77.0)	50.0 + / - 2.3%				




Fig. 18 – 10K Thermistor Resistance Versus Temperature




Fig. 19 – 50K Thermistor Resistance Versus Temperature

If the outdoor air or coil thermistor should fail, the control will flash the appropriate fault code (see Table 6).

**IMPORTANT:** The outdoor air thermistor, coil thermistor and suction thermistor should be factory mounted in the final locations. Check to ensure thermistors are mounted properly (See Fig. 20, 21, 22 and 23).

#### **Thermistor Sensor Comparison**

The control continuously monitors and compares the outdoor air temperature sensor and outdoor coil temperature sensor to ensure proper operating conditions. The comparison is:


In cooling if the outdoor air sensor indicates ≥ 10°F (≥ 5.6°C) warmer than the coil sensor (or) the outdoor air sensor indicates ≥ 25°F (≥ 12°C) cooler than the coil sensor, the sensors are out of range.

If the sensors are out of range, the control will flash the appropriate fault code as shown in Table 6.

The thermistor comparisons are not performed during low ambient cooling.

#### **Outdoor Coil Thermistor**

The outdoor coil thermistor is a 10Kohm resistor used for multiple system operations. It provides the coil/liquid line temperature to the AC unit board and Observer<sup>®</sup> Wall Control. Low ambient operation, and assistance with OAT temperature measurement are some of the functions. The sensor must be securely mounted to the tube connecting the coil and distributor. See Fig. 21 for proper placement. See Table 4 for proper resistances.





A14328

A11142

Fig. 20 – Outdoor Coil Thermistor (OCT) Attachment (On Distributor Tube)

OAT Thermistor must be locked in place with spherical nib end facing towards the front of the control box





#### Suction Thermistor (OST)


Suction Thermistor is used to accurately measure suction temperature and must be secured on the suction tube and aligned longitudinally to the vertical surface of the tube axis (see Fig. 22).

# **A** CAUTION

#### UNIT DAMAGE HAZARD

Failure to follow this caution may result in equipment damage or improper operation.

In order to minimize the ambient influence, make sure the thermistor curved surface hugs the pipe surface and is secured tight using the wire tie fished through the original slot insulating polymer body.



A14023 Fig. 22 – Suction Thermistor (OST) Attachment (On Suction Tube)

#### **Discharge Thermistor (ODT)**

Discharge Thermistor is used for protection against over temperature of the compressor. The ODT is located on the compressor discharge stub–out (see Fig. 23). Maximum ODT is approximately 240  $F^{\circ}$  (116  $C^{\circ}$ ).




Fig. 23 - Discharge Thermistor (ODT)

#### Variable Speed Compressor Winding Resistance

This compressor operates with 3–phase variable frequency PWM variable voltage. For troubleshooting certain fault codes related to compressor resistances, follow these steps:

- 1. Disconnect compressor power leads from the inverter MOC terminals, U (YEL), V (RED), and W (BLK).
- 2. Measure the resistance between YEL to RED, YEL to BLK, and RED to BLK and compare to Table 5 values. Each resistance set should be equal.
- 3. Measure the resistance to ground for each lead.
- 4. If the resistances check out, reconnect power leads to appropriate terminal.
- 5. If the resistances appear to be abnormal, it will be necessary to measure the resistance at the compressor fusite terminals.
- 6. During the removal of the compressor fusite cap, do not remove the RTV sealant. Remove the harness plug, measure the resistances, and compare to Table 5.
- 7. Special care will need to be taken with the replacement of the compressor fusite cap. Make sure the two holes in the compressor fusite terminal box are still full of RTV sealant before the cap is reinstalled. The factory RTV can be reused as long as none of it has been removed during the cap removal.

8. Reinstall compressor sound blanket making sure discharge thermistor and compressor power harness are routed as they were from the factory

#### Table 5 – Variable Speed Compressor Resistance (winding resistance at 70°F ± 20°F)

WINDING	MODEL CVA9, HVA9, TVA9 (OHMs)						
WINDING	24 25 36 37, 48 49,						
Between terminals	1.13	.59	.59	.37	.24		
Between terminal & ground	>1 mega						

# **A** CAUTION

#### UNIT DAMAGE HAZARD

Failure to follow this caution may result in equipment damage and/or improper operation.

Do not use Meggar for measuring the winding resistance.

# **A** CAUTION

#### UNIT DAMAGE HAZARD

Failure to follow this caution may result in equipment damage and/or improper operation.

To maintain water integrity of the compressor fusite terminal box, the two holes in outer ring need to be full of RTV sealant.

#### Fan Motor

If verification of proper operation is required for the fan motor used in this unit, follow these steps:

- 1. Disconnect fan motor connector from control board.
- 2. Measure resistance between any 2 of the 3 leads present.
- 3. Compare measurement to values below

Fan Motor Resistance				
Unit Size Resistance (Ohms)				
24	21.2			
25, 36, 37, 48, 49, 60	11.1			

Occasionally the unit may become unresponsive due to certain combinations of previous fault codes. There may not be anything wrong with the unit or components. The unit may require a high voltage power cycling for at least 2 minutes or longer to clear the condition. If the condition persists, conduct further troubleshooting per the service manual.

#### **Status Codes**

 $\hat{\Lambda}$ 

Table 6 shows the status codes flashed by the amber status light. Most system problems can be diagnosed by reading the status code as flashed by the amber status light on the control board.

The codes are flashed by a series of short and long flashes of the status light. The short flashes indicate the first digit in the status code, followed by long flashes indicating the second digit of the error code.

The short flash is 0.25 seconds ON and the long flash is 1.0 second ON. Time between flashes is 0.25 seconds. Time between short flash and first long flash is 1.0 second. Time between code repeating is 2.5 seconds with LED OFF.

Codes are easily read from Observer<sup>®</sup> Wall Control.

#### EXAMPLE:

3 short flashes followed by 2 long flashes indicates a 32 code. Table 6 shows this to be low pressure switch open.

#### Table 6 – Troubleshooting

	SERV	CE	
AMBER LED DESCRIPTION	* FLASH CODE (Amber LED)	RESET TIME (Minimum) Minutes	* * TYPE
Standby	ON, no flash		
Variable Capacity Mode	1, pause		
Variable Speed Range Cutback	1 (2 sec ON), longer pause (1 second OFF)		
Invalid Model Plug/Inverter Size	25	N/A	System Malfunction
High Pressure Switch Open	31	6	Local
Low Pressure Trip	32	6	Local
Lost Inverter Communications	33	6	Local
Brownout Event	46	6	Local
Lost Inverter Communications	48	6	System Malfunction
Compressor Over Current Fault	49	6	Local
Outdoor Air Temp Sensor Fault	53	N/A	Fault
Suction Temp Sensor Fault	54	N/A	Fault
Coil Temp Sensor Fault	55	N/A	Fault
OAT-OCT Thermistor Out of Range	56	N/A	Local
Suction Pressure Sensor Fault	57	N/A	Fault
Discharge Temperature Out of Range Event	59	15	Local
Fan Inverter Fault	61	6	Local
Fan Inverter Temp High	62	N/A	Local
Fan Inverter Current Fault	63	6	Local
D C Voltage Low - SPD Limiting	65	N/A	Local
Outdoor Fan Dropped Out	66	6	Local
Stator Heater Fault	67	6	Local
10 Minute Stage 2 Warmup Delay	68	10	Event
Inverter / Compressor Internal Fault	69	15	System Malfunction
Compressor Dropped Out	71	6	Local
Suction Over Temperature Event	72	15	Local
Discharge Temp Out of Range Lockout	74	2 Hours	System Malfunction
Maximum Power Mode-Temp	75	N/A	Local
Fan Inverter Lockout	76	2 Hours	System Malfunction
Maximum Power Mode-Comp Current	77	N/A	Local
Compressor/Inverter Fault	79	6	Local
Suction Over Temp Lockout	82	4 Hours	System Malfunction
Low Pressure Lockout for 4 hours	83	4 Hours	System Malfunction
High Pressure Lockout for 4 hours	84	4 Hours	System Malfunction
Fan Inverter Temp Lockout	85	15	System Malfunction
Fan Inverter Current Lockout	86	6	System Malfunction
Compressor/Inverter Lockout	88	2 Hours	System Malfunction
Inverter VDC-Out Over Voltage Event	91	6	Local
Inverter VDC-Out Under Voltage Event	92	6	Local
230VAC Under Voltage Event	93	6	Local
230VAC Over Voltage Event	94	6	Local
Compressor Over Current Lockout	95	2 Hours	System Malfunction
VDC Under Voltage Lockout	96	2 Hours	System Malfunction
VDC Over Voltage Lockout	97	2 Hours	System Malfunction
High Torque Event	98	N/A	Local
High Torque Lockout	99 OFF	2 Hours N/A	System Malfunction No Power
* Short Flashes indicate the firs by long flashes indicating the se * * Local Faults displayed only on generic wall control or re	t digit in the econd digit on amber L	e status cod of the statu _ED and not	e followed s code.
		,	4-101 REV. A

# **FINAL CHECKS**

**IMPORTANT:** Before leaving job, be sure to do the following:

- 1. Ensure that all wiring is routed away from tubing and sheet metal edges to prevent rub-through or wire pinching.
- 2. Ensure that all wiring and tubing is secure in unit before adding panels and covers. Securely fasten all panels and covers.
- 3. Tighten service valve stem caps to 1/12-turn past finger tight.
- 4. Leave User's Manual with owner. Explain system operation and periodic maintenance requirements outlined in manual.

# CARE AND MAINTENANCE

For continuing high performance and to minimize possible equipment failure, periodic maintenance must be performed on this equipment.

Frequency of maintenance may vary depending upon geographic areas, such as coastal applications. See Owner's Manual for information.

ABELS	
ICAL L/	
TECHNI	

A serie of column state interaction of the state in the state interaction of the state interactinant of the state interaction of the state interaction of the st									001	0110		W ACC	1:+ N E		***V C	0+0	202		200,	2 u																	
Image:									170	210		Jutdoor J	Ambient	Tempera	ture - D	egrees F,	Dry Bul			ß																	
Fit Many and the parture - bage in the parture - ba				ſ	65				75			85		F		95		┢		105		-		115#													
F. F. Mode         T         F												Entering	Indoor 7	emperat	ure - De	grees F,	Wet Bulk					-															
CHA         Tend         CHA         Fer         Fer </th <th>STAGE-</th> <th>-5 Mode</th> <th>72</th> <th>67</th> <th>63††</th> <th></th> <th>72</th> <th>67</th> <th>63††</th> <th></th> <th>72</th> <th></th> <th>63††</th> <th>57</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th>72</th> <th>67</th> <th>63††</th> <th>57</th>	STAGE-	-5 Mode	72	67	63††		72	67	63††		72		63††	57								72	67	63††	57												
Imate         Imate <t< th=""><th></th><th>SCFM</th><th></th><th>2</th><th></th><th>-</th><th></th><th></th><th>- ف</th><th></th><th></th><th></th><th></th><th></th><th>t t</th><th>õ -</th><th></th><th></th><th>-</th><th>4</th><th>-</th><th></th><th></th><th></th><th></th></t<>		SCFM		2		-			- ف						t t	õ -			-	4	-																
Image         Display         Display <thdisplay< th=""> <thdisplay< th=""> <thdi< th=""><th></th><th>MBh†</th><th>30.22</th><th>27.45</th><th></th><th>_</th><th>28.48</th><th>_</th><th>_</th><th>22.54</th><th>26.87</th><th></th><th>-</th><th></th><th></th><th>-</th><th>-</th><th>-</th><th></th><th>_</th><th>-</th><th>96</th><th></th><th></th><th></th></thdi<></thdisplay<></thdisplay<>		MBh†	30.22	27.45		_	28.48	_	_	22.54	26.87		-			-	-	-		_	-	96															
Hursy         5:8 </th <th></th> <th>S/T‡</th> <th>0.52</th> <th>0.70</th> <th></th> <th>-</th> <th></th> <th></th> <th>0.72</th> <th>1.00</th> <th>0.52</th> <th>0.70</th> <th>0.72</th> <th></th> <th>-</th> <th></th> <th>-</th> <th>-</th> <th>_</th> <th>_</th> <th>_</th> <th>0</th> <th></th> <th></th> <th></th>		S/T‡	0.52	0.70		-			0.72	1.00	0.52	0.70	0.72		-		-	-	_	_	_	0															
	De-Humidity	AMPS*	5.78	5.82					6.85	6.84	7.99	7.95	7.92		-		-		_	_	_	34															
		HI PR	256	251		246	293	289	285	283	335	330	327									7															
CFM         Activation         Activation <th></th> <th>LO PR</th> <th>155</th> <th>141</th> <th></th> <th>124</th> <th>155</th> <th>141</th> <th>131</th> <th>124</th> <th>156</th> <th>142</th> <th>132</th> <th>124</th> <th>_</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th>1</th> <th></th> <th></th> <th></th>		LO PR	155	141		124	155	141	131	124	156	142	132	124	_							1															
MBH         30.4         36.12         26.11         26.11         26.14         26.11         2		SCFM		æ					N)			82				Ñ				825				825													
811         0.54         0.74         0.76 <th< th=""><th></th><th>₩Bh†</th><th>30.94</th><th>28.12</th><th></th><th></th><th></th><th></th><th></th><th></th><th>27.93</th><th>_</th><th></th><th></th><th></th><th>-</th><th></th><th></th><th></th><th></th><th></th><th>35 23.36</th><th>36 21.24</th><th>4 19.74</th><th>19.93</th></th<>		₩Bh†	30.94	28.12							27.93	_				-						35 23.36	36 21.24	4 19.74	19.93												
AMPS         5:9         6:0         1:0         7:0 </th <th>Efficiency</th> <th>S/T‡</th> <th>0.54</th> <th>0.73</th> <th></th> <th></th> <th>0.55</th> <th></th> <th>0.77</th> <th>1.00</th> <th>0.55</th> <th>0.76</th> <th>0.79</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th>_</th> <th></th> <th>1.00</th>	Efficiency	S/T‡	0.54	0.73			0.55		0.77	1.00	0.55	0.76	0.79										_		1.00												
Intro         100<		AMPS*	5.94	5.99		6.04	7.08		7.09	7.08	8.29	8.25	8.22							-		·		•	12.10												
		HI PR	257	252		248	296	291	287	286	338	333	329									1 487		475	476												
SCFM         All         All<		LO PR	159	145		131	161	147	137	133	163	149	138	136	165			-	-			2 169	9 154	144	145												
IBDIT         30.58         27.54         25.64         25.85         26.41         25.75         27.15         27.65         25.75         27.15         27.75         27.15         27.75         27.15         27.75 <t< th=""><th></th><th>SCFM</th><th></th><th>Ĩ</th><th>48</th><th></th><th></th><th>Ő</th><th>40</th><th></th><th></th><th>83</th><th></th><th>ŀ</th><th></th><th>825</th><th></th><th></th><th></th><th>825</th><th></th><th></th><th>_</th><th>825</th><th></th></t<>		SCFM		Ĩ	48			Ő	40			83		ŀ		825				825			_	825													
S17         0.55         0.74         0.77         0.76         0.76         0.76         0.76         0.76         0.76         0.76         0.76         0.76         0.76         0.76         0.76         0.76         0.76         0.76         0.76         0.76         0.76         0.76         0.86         0.76 <th< th=""><th></th><th>₩Bh†</th><th>30.58</th><th>27.95</th><th></th><th>-</th><th>_</th><th></th><th>-</th><th>24.23</th><th>27.74</th><th></th><th></th><th>_</th><th>-</th><th>-</th><th>-</th><th>-</th><th>-</th><th></th><th>-</th><th>11 23.41</th><th>11 21.35</th><th>5 19.87</th><th>20.04</th></th<>		₩Bh†	30.58	27.95		-	_		-	24.23	27.74			_	-	-	-	-	-		-	11 23.41	11 21.35	5 19.87	20.04												
		\$/T‡	0.55	0.74		1.00	0.55	1	0.78	1.00	0.56	0.77	0.79		-		-	-	-				9 0.82	0.84	1.00												
H PR         266         252         249         277         234         331         330         355         311         470         473         474         474         474         474         474         474         474         474         474         474         474         474         474         474         474         475         474         475         474 </th <th>Maximum</th> <th>AMPS*</th> <th>5.83</th> <th>5.92</th> <th></th> <th>5.98</th> <th>6.99</th> <th>-</th> <th>7.07</th> <th>7.07</th> <th>8.22</th> <th>8.23</th> <th>8.23</th> <th></th> <th></th> <th></th> <th></th> <th>1</th> <th></th> <th></th> <th>-</th> <th>78 12.42</th> <th>Ľ.</th> <th>9 12.19</th> <th>12.21</th>	Maximum	AMPS*	5.83	5.92		5.98	6.99	-	7.07	7.07	8.22	8.23	8.23					1			-	78 12.42	Ľ.	9 12.19	12.21												
		HI PR	256	252		247	295	291	288	287	338	334	331					-						482	482												
		LO PR	160	146		132	162	148	137	134	163	149	139	137	165		_	_	-		-	2 168	3 154	143	145												
OLIGOOR Ambient Temperature - Degrees F, Dry Bulb         - T         - T         - OLIGOOR Ambient Temperature - Degrees F, Dry Bulb           F. Mode         T         7         - A         - S         - S         - S         - S									925	Size	Outd	oor W	/ith F(	CM4X	48***	L Sta	ge 5	oopu	r Coo	ling																	
4         6         7         8         106           ST         10         10         10         106         106         106         106         106         106          106 <th <<="" colspan="12" th=""><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th>ĺ</th><th>Jutdoor /</th><th>Ambient</th><th>Tempera</th><th>ture - D</th><th>egrees F,</th><th>Dry Bul</th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th></th>	<th></th> <th>ĺ</th> <th>Jutdoor /</th> <th>Ambient</th> <th>Tempera</th> <th>ture - D</th> <th>egrees F,</th> <th>Dry Bul</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th>																						ĺ	Jutdoor /	Ambient	Tempera	ture - D	egrees F,	Dry Bul								
F interim prindical metric - Degrees f, wet Builo           F is it is it is is in the fait is interimed and the fait is int					65				75			85				95				105				115#													
E-5 Mode         72         67         72         67         6314         57         72         67         6314         57         72         67         6314         57         72         67         6314         57         72         63         72         63												Entering	Indoor 7	emperat	ure - De	grees F,	Wet Bulk																				
SCFM         TO8         663         673 </th <th>STAGE-</th> <th>-5 Mode</th> <th>72</th> <th>29</th> <th>63††</th> <th></th> <th>72</th> <th>67</th> <th>63††</th> <th>57</th> <th>72</th> <th></th> <th>63††</th> <th>57</th> <th>72</th> <th></th> <th>-</th> <th></th> <th></th> <th></th> <th></th> <th>72</th> <th>. 67</th> <th>63††</th> <th>57</th>	STAGE-	-5 Mode	72	29	63††		72	67	63††	57	72		63††	57	72		-					72	. 67	63††	57												
MBht         29.49         68.71         57.13         23.77         27.98         55.55         22.41         26.54         21.23         20.10         0.73         1.00         0.57         0.79         0.81           SIT\$         0.52         0.70         0.73         1.00         0.57         0.70         0.73         1.00         0.57         0.70         0.71         7.10         7.14		SCFM		-	12				ò			ŝ				õ				608																	
SfT $0.52$ $0.70$ $0.72$ $0.00$ $0.52$ $0.70$ $0.72$ $1.00$ $0.57$ $0.70$ $0.77$ $0.70$ $0.71$ <th></th> <th>₩Bh†</th> <th>29.49</th> <th>26.97</th> <th></th> <th>-</th> <th>27.98</th> <th>-</th> <th>-</th> <th>22.41</th> <th>26.55</th> <th>-</th> <th></th> <th></th> <th>-</th> <th></th> <th>-</th> <th></th> <th></th> <th></th> <th></th> <th>12</th> <th></th> <th></th> <th></th>		₩Bh†	29.49	26.97		-	27.98	-	-	22.41	26.55	-			-		-					12															
AMP5* $4.64$ $4.90$ $5.06$ $5.18$ $5.79$ $5.99$ $6.12$ $6.12$ $6.19$ $6.97$ $7.10$ $7.11$ $8.15$ $8.23$ $8.26$ $7.02$ $7.10$ $7.14$ HPR $237$ $234$ $237$ $237$ $237$ $237$ $271$ $259$ $231$ $315$ $315$ $311$ $365$ $360$ $358$ $396$ $394$ $392$ LOPR $160$ $145$ $134$ $126$ $134$ $127$ $150$ $275$ $27.50$ $28.99$ $26.45$ $24.76$ $27.50$ $27.60$ $28.89$ $26.45$ $24.76$ $27.50$ $27.60$ $28.99$ $26.45$ $24.76$ $27.50$ $27.51$ $26.72$ $7.10$ $7.14$ SCFM $30.15$ $27.61$ $25.71$ $25.00$ $28.89$ $26.45$ $24.67$ $24.76$ $27.52$ $26.76$ $28.90$ $26.49$ $29.75$ $27.52$ $27.56$ $28.90$ $26.78$ $29.76$ $27.72$ $27.72$ $27.72$ $27.72$ $27.72$ $27.72$ $27.72$ $27.72$ $27.72$ $27.76$ $27.72$ $27.76$ $27.76$ $27.72$ $27.72$ $27.76$ $27.72$ $27.76$	Comfort	\$/T‡	0.52	0.70			0.52		0.72	1.00	0.52	0.70	0.72									0															
HPR         237         234         232         231         275         273         271         269         319         311         365         362         396         394         392           CDPR         160         145         134         127         159         145         134         127         170         155         144           SCFM $\mathbf{x}$	- De-Humidity	AMPS*	4.64	4.90		5.18	5.79		6.12	6.19	6.97	7.10	7.18									4															
LOPR         160         145         134         127         150         145         134         127         170         155         144           SCFM $30.15$ 27.61         25.77         25.6         153         145         154         127         170         155         144           SCFM $30.15$ 27.61         25.77         25.00         28.89         26.45         24.00         27.59         25.24         23.15         26.25         24.00         22.18         24.94         22.78         21.22           MBh*         0.54         0.77         100         0.55         0.78         1.00         0.55         0.70         1.00         0.57         0.80         0.80         26.43         24.91         23.9         36.9         36.9         36.9         36.1         3		HI PR	237	234		<sup>231</sup>	276		271	269	319	315	313									5															
SCFM $32.5$ $32.6$ </th <th></th> <th>LO PR</th> <th>160</th> <th>145</th> <th>-</th> <th>127</th> <th>159</th> <th>145</th> <th>134</th> <th>126</th> <th>159</th> <th>145</th> <th>134</th> <th>126</th> <th></th> <th>_</th> <th>_</th> <th></th> <th>_</th> <th>_</th> <th>_</th> <th>4</th> <th></th> <th></th> <th></th>		LO PR	160	145	-	127	159	145	134	126	159	145	134	126		_	_		_	_	_	4															
MBht         30.15         27.51         25.00         28.89         26.45         24.05         27.50         28.315         24.05         24.00         22.38         22.18         24.94         27.58         21.2           S/T         0.54         0.77         100         0.55         0.76         100         0.55         0.80         100         0.57         0.80         100         0.57         0.80         0.82         8.40         8.2.48         21.66         9.64           AMPS*         4.64         4.92         5.11         5.16         5.82         6.03         6.17         6.20         7.02         1.71         7.27         7.28         8.40         8.33         956         9.61         9.64           HPR         241         130         164         150         137         167         152         141         139         169         154         170         155         144           MBr         212         516         151         140         137         167         152         141         139         169         154         142         170         155         144           MBr         30.29         51.7         51.8		SCFM			21				Ñ.			21				825				825				825													
S/T $0.54$ $0.77$ $1.00$ $0.55$ $0.78$ $1.00$ $0.57$ $0.70$ $1.00$ $0.57$ $0.80$ $1.00$ $0.57$ $0.80$ $1.00$ $0.57$ $0.80$ $1.00$ $0.57$ $0.80$ $1.00$ $0.57$ $0.80$ $1.00$ $0.57$ $0.80$ $0.81$ $9.64$ AMPS* $4.64$ $4.92$ $5.11$ $5.16$ $5.82$ $6.03$ $6.17$ $6.20$ $7.02$ $7.17$ $7.28$ $8.24$ $8.33$ $9.56$ $9.51$ $9.14$ AMPS* $164$ $150$ $138$ $135$ $167$ $157$ $157$ $128$ $156$ $9.51$		MBh†	30.15		_	-			_	24.09	27.59			_	_	-	-	-	-		-				20.15												
AMPS*         4.64         4.92         5.11         5.16         5.82         6.03         6.17         6.20         7.02         7.17         7.27         7.28         8.24         8.35         9.56         9.51         9.54           HIPK         241         150         138         135         160         151         5.10         5.72         7.78         8.24         8.35         8.40         8.39         9.56         9.51         9.54           LOPR         164         150         138         135         160         151         140         137         167         152         141         139         169         154         142         155         141           SCFM         stor           MBht         30.29         5.17         5.87         25.18         2.473         2.775         2.738         2.8.57         2.40         2.2.90         2.7.91         2.7.40           ST         0.55         0.77         10.0         0.56         0.78	Efficiency	S/T‡	0.54	0.74		1.00			0.78	1.00	0.56	0.77	0.79												1.00												
HPR         241         236         234         280         276         274         273         313         316         316         363         363         363         416         413         411           LOPR         164         150         138         135         166         151         140         137         167         152         141         139         169         154         142         170         155         144           SCFM <th style<="" th="" tr<=""><th>6</th><th>AMPS*</th><th>4.64</th><th>4.92</th><th></th><th>5.16</th><th></th><th></th><th>6.17</th><th>6.20</th><th>7.02</th><th>7.17</th><th>7.27</th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th>,</th><th></th><th></th><th>10.83</th></th>	<th>6</th> <th>AMPS*</th> <th>4.64</th> <th>4.92</th> <th></th> <th>5.16</th> <th></th> <th></th> <th>6.17</th> <th>6.20</th> <th>7.02</th> <th>7.17</th> <th>7.27</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th>,</th> <th></th> <th></th> <th>10.83</th>	6	AMPS*	4.64	4.92		5.16			6.17	6.20	7.02	7.17	7.27									,			10.83											
LOPR         164         150         138         135         166         151         140         157         157         159         169         154         142         170         155         144           SCFM             150         153         154         153         154         142         170         155         144		HI PR	241	238		234	280		274	273	323	319	316												467												
SCFM         #40         E40         #50         #50         #50         #50         #21         #23         #21         #21         #23         #21         #21         #23         #23         #21         #21         #21         #21         #23         #21         212         #21         212         211         212         211         212         211         212         211         212         211         212         211         212         211         212         211         212         211         212         211         212         211         212         211         212         211         212         212         211         212         211         212         211         212         212 </th <th></th> <th>LO PR</th> <th>164</th> <th>150</th> <th></th> <th>135</th> <th>166</th> <th></th> <th>140</th> <th>137</th> <th>167</th> <th>152</th> <th>141</th> <th>139</th> <th>169</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th>5 172</th> <th>2 157</th> <th>_</th> <th>148</th>		LO PR	164	150		135	166		140	137	167	152	141	139	169							5 172	2 157	_	148												
MBht         30.29         27.73         25.87         26.53         23.87         26.30         24.04         22.40         22.80         24.99         22.81         21.24           S/T         0.55         0.77         1.00         0.56         0.77         1.00         0.56         0.77         0.80         1.00         0.57         0.80         1.00         0.57         0.80         1.00         0.57         0.80         1.00         0.57         0.80         1.00         0.57         0.80         1.00         0.57         0.80         1.00         0.57         0.80         0.82         0.841         8.41         9.58         9.65		SCFM					_		50							825				825				æ													
S/T +       0.55       0.77       1.00       0.56       0.78       0.77       0.80       1.00       0.57       0.80       1.00       0.57       0.80       0.57       0.80       0.87       0.80       0.87       0.81       0.81       0.81       0.81       0.81       0.81       0.82       0.82       0.82       0.82       0.83       8.41       8.41       9.58       9.63       9.65         AMPS*       4.65       4.93       5.12       5.17       5.84       6.05       6.19       6.22       7.04       7.30       7.30       8.25       8.36       8.41       8.41       9.58       9.63       9.65         HIPR       242       238       281       277       274       274       320       317       317       370       367       364       417       413       411         LOPR       165       150       135       168       153       142       141       170       155       143       170       155       144       170       155       170       155       144       145       144       145       144       145       144       141       170       155       147       413		₩Bh†	30.29						_	24.33	27.75					-	-				-				20.17												
AMPS*       4.65       4.93       5.12       5.17       5.84       6.05       6.19       6.22       7.04       7.30       7.30       8.25       8.36       8.41       9.58       9.63       9.65         HIPR       242       238       236       237       274       274       323       320       317       317       370       367       364       3417       413       411         LOPR       155       150       139       135       167       152       140       138       168       153       141       170       155       143       155       144	miminem	\$/T‡	0.55	0.75		1.00	0.56		0.78	1.00	0.56	0.77	0.80												1.00												
242 238 236 235 281 277 274 274 323 320 317 317 370 367 364 364 417 413 411 411 170 155 150 139 135 143 155 144 155 140 138 168 153 142 141 170 155 143 143 170 155 144		AMPS*	4.65	4.93		5.17	5.84		6.19	6.22	7.04	7.20	7.30									4 10.88	38 10.87	7 10.84	10.84												
165 150 139 135 167 152 140 138 168 153 142 141 170 155 143 143 170 155 143		HI PR	242	238	_	235	281	277	274	274	323	320	317				_	_	_					_	468												
		LO PR	165	150		135	167	152	140	138	168	153	142		170							5 172	2 157	146	148												

Output for the probability of the p									020	Size	<b>Outo</b>	Nor V	ith FC		1,8***	Stac	10 <u>5</u> lr	door	Cool	Du																					
												utdoor A	mbient	Temperat	ure - De	grees F,	Dry Bulb			P																					
CT M         T         F				9	9				75			85		╞		<b>3</b> 2				105				115#																	
F574         641         7         7         6         641         5         7         6         641         5         7												Entering	Indoor To	emperatu	ire - Deț	trees F, V	Vet Bulb					-																			
Holi         Holi </th <th>STAGE-</th> <th>5 Mode</th> <th>72</th> <th>29</th> <th>63††</th> <th>57</th> <th>72</th> <th>67</th> <th>63††</th> <th>57</th> <th>72</th> <th></th> <th>63††</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th>63††</th> <th></th> <th>72</th> <th>67</th> <th>63††</th> <th>57</th>	STAGE-	5 Mode	72	29	63††	57	72	67	63††	57	72		63††							63††		72	67	63††	57																
wttp         13:0:0:0:0:0:0:0:0:0:0:0:0:0:0:0:0:0:0:0		SCFM		6	<u><u></u></u>			8	87			14		-						÷																					
Mit         Dis         Dis <th></th> <th>MBh†</th> <th>43.26</th> <th>39.72</th> <th></th> <th>34.42</th> <th></th> <th></th> <th>35.10</th> <th>32.41</th> <th></th> <th></th> <th></th> <th>-</th> <th></th>		MBh†	43.26	39.72		34.42			35.10	32.41				-																											
Mbr.         65         6	Comfort	S/T‡	0.51	0.68	0.70	1.00	0.51	0.67	0.70	1.00	0.51			-				-			1.00																				
Und         SS	+ Do Unmidity	AMPS*	8.54	8.70	8.80	8.87	10.31	10.38		10.42				-				+																							
UDR         120         130 <th></th> <th>HI PR</th> <th>263</th> <th>259</th> <th>256</th> <th>254</th> <th>304</th> <th>300</th> <th>297</th> <th>294</th> <th>350</th> <th>345</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th>-</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th>		HI PR	263	259	256	254	304	300	297	294	350	345						-																							
SFH         100 <th></th> <th>LO PR</th> <th>152</th> <th>138</th> <th>128</th> <th>118</th> <th>152</th> <th>138</th> <th>128</th> <th>117</th> <th>152</th> <th>138</th> <th></th> <th>-</th> <th></th> <th></th> <th></th> <th>-</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th>		LO PR	152	138	128	118	152	138	128	117	152	138		-				-																							
With         132         77         67         73 <th< th=""><th></th><th>SCFM</th><th></th><th>9 P</th><th>50</th><th></th><th></th><th>Ĕ</th><th>)5<b>0</b></th><th></th><th></th><th>105(</th><th>6</th><th></th><th></th><th>1050</th><th></th><th> </th><th></th><th>1050</th><th></th><th></th><th></th><th>1050</th><th></th></th<>		SCFM		9 P	50			Ĕ	)5 <b>0</b>			105(	6			1050				1050				1050																	
NT         B22         D/0         D/2         D/1         D/2         D/2 <thd 2<="" th="">         D/2         <thd 2<="" th=""> <thd 2<="" th=""> <thd 2<="" th=""></thd></thd></thd></thd>		MBh†	43.98	40.39			-			34.31				-				-				1	31.25	29.21	28.61																
MBF         Bit         Bit <th></th> <th>S/T‡</th> <th>0.52</th> <th>0.70</th> <th>0.72</th> <th>1.00</th> <th>0.53</th> <th>0.71</th> <th>0.73</th> <th>1.00</th> <th>0.53</th> <th></th> <th></th> <th>-</th> <th></th> <th></th> <th></th> <th>-</th> <th></th> <th></th> <th>1.00</th> <th>0.56</th> <th>0.76</th> <th>0.78</th> <th>1.00</th>		S/T‡	0.52	0.70	0.72	1.00	0.53	0.71	0.73	1.00	0.53			-				-			1.00	0.56	0.76	0.78	1.00																
HHR         284         286         286         387         344         346         341         341         351 <th>Efficiency</th> <th>AMPS*</th> <th>8.60</th> <th>8.76</th> <th>8.87</th> <th>8.93</th> <th>10.46</th> <th></th> <th></th> <th>10.60</th> <th></th> <th></th> <th></th> <th>-</th> <th></th> <th></th> <th></th> <th>-</th> <th></th> <th></th> <th></th> <th>-</th> <th>19.04</th> <th>18.84</th> <th>18.77</th>	Efficiency	AMPS*	8.60	8.76	8.87	8.93	10.46			10.60				-				-				-	19.04	18.84	18.77																
UDR         165         12         131         123         135         133		HI PR	264	260	257	255	306	301	298	296	352	347		+				+			439	510	504	501	500																
SFH         1000         1200		LO PR	156	142	131	123	157	143	133	126	159	145		-				+			134	164	150	139	137																
HIP         4397         44.2         73.16         53.6         43.5         73.1         73.9         73.0 <th< th=""><th></th><th>SCFM</th><th></th><th>۹ ا</th><th>80</th><th></th><th></th><th>1</th><th>00</th><th></th><th></th><th>120</th><th>6</th><th></th><th></th><th>1200</th><th></th><th></th><th></th><th>1050</th><th></th><th></th><th></th><th>1050</th><th></th></th<>		SCFM		۹ ا	80			1	00			120	6			1200				1050				1050																	
811         103         0.71         0.73         0.70         0.75         0.70         0		MBh†	43.97	40.42			-		36.72	35.61				-								-	31.14	29.14	28.55																
AMPS         E60         B75         B87         B87         IG51         IG11         IG1		S/T‡	0.53	0.71	0.73	1.00	0.55	0.74	0.77	1.00	0.55											0.56	0.76	0.78	1.00																
HP         283         284         364         361	Maximum	AMPS*	8.60	8.76	8.87	8.92	10.61	10.71	10.77	10.77				-				-				_	18.98	18.78	18.71																
LOPR         157         143         128         163         143         136         163         143         136         160         137         134         165         150         133         155         160         137         135         165         150         133         155         151 <th></th> <th>HI PR</th> <th>263</th> <th>259</th> <th>256</th> <th>254</th> <th>306</th> <th>302</th> <th>298</th> <th>297</th> <th></th> <th></th> <th></th> <th>_</th> <th></th> <th></th> <th></th> <th>+</th> <th></th> <th></th> <th></th> <th>_</th> <th>502</th> <th>499</th> <th>497</th>		HI PR	263	259	256	254	306	302	298	297				_				+				_	502	499	497																
337 Size Outdoor With FCM4X60***L Stage 5 Indoor Cooling           Size Outdoor Ambient temperature - Degrees I, DY Bulb           65         7         Size Outdoor Ambient temperature - Degrees I, DY Bulb           For Mode         7         Size Outdoor Ambient temperature - Degrees I, DY Bulb           For Mode         7         Size Outdoor Ambient temperature - Degrees I, DY Bulb           For Mode         7         Size Outdoor Ambient temperature - Degrees I, DY Bulb           For Mode         7         Size Outdoor Ambient temperature - Degrees I, DY Bulb           For Mode         7         Size Outdoor Ambient temperature - Degrees I, DY Bulb           For Mode         7         Size Size Size Size Size Size Size Size		LO PR	157	143	132	125	161	147	136	132	163	148		-				+			134	165	150	139	137																
A control of control of control formperature - Degrees f. Un guide         A control of control for control for control of control for control of control for control of control for contro										Sizo	Citter	W N	ith EC	MAX.	***05		19 5 10	100p																							
Output the matrix of										210		the local state of the local sta	mhiant							מ																					
Fig. 1         10 <th <="" colspan="16" th=""><th></th><th></th><th></th><th>ű</th><th>u</th><th></th><th></th><th>ſ</th><th>ų</th><th></th><th></th><th>4 100010</th><th></th><th></th><th></th><th>dicco i,</th><th></th><th>╞</th><th></th><th>105</th><th></th><th>_</th><th></th><th>1464</th><th></th></th>	<th></th> <th></th> <th></th> <th>ű</th> <th>u</th> <th></th> <th></th> <th>ſ</th> <th>ų</th> <th></th> <th></th> <th>4 100010</th> <th></th> <th></th> <th></th> <th>dicco i,</th> <th></th> <th>╞</th> <th></th> <th>105</th> <th></th> <th>_</th> <th></th> <th>1464</th> <th></th>																			ű	u			ſ	ų			4 100010				dicco i,		╞		105		_		1464	
Service         2         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         57         72         67         631         72         67         631         72         63         33.2         23.2         33.4         33.4         33.4         33.4         33.4         33.4         33.4         33.4         33.4         33.4         33.4         33.4         33.4         33.4         33.4         33.4         33.4         33.4         33.4 <t< th=""><th></th><th></th><th></th><th></th><th>2</th><th></th><th></th><th></th><th>2</th><th>1</th><th>ľ</th><th>201-01-</th><th>T and the</th><th></th><th></th><th>90 1 1 1</th><th>4 D. 16</th><th>_</th><th></th><th>601</th><th></th><th></th><th></th><th>#C11</th><th></th></t<>					2				2	1	ľ	201-01-	T and the			90 1 1 1	4 D. 16	_		601				#C11																	
F-5 Mode         72         671         5311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         77         72         67         6311         77         72         67         6311         77         72         67         6311         77         72         67         6311         77         72         67			i	-		ł	i			1		-urering		emperau	ian - au	ticees r.' /	ver pulo	ŀ	ŀ				;																		
90         923         923         924         925         912         912         912         913         914 <th>STAGE-</th> <th>5 Mode</th> <th>72</th> <th>67</th> <th>63††</th> <th></th> <th>22</th> <th>67</th> <th>63††</th> <th>57</th> <th>72</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th>63†1</th> <th></th> <th>72</th> <th>67</th> <th>63††</th> <th>57</th>	STAGE-	5 Mode	72	67	63††		22	67	63††	57	72									63†1		72	67	63††	57																
MBht         43.10         39.20         36.40         3.42         3.765         3.442         3.247         3.823         3.47         3.251         3.047         2.829         2.663         1.073         1.00         1.267         1.00         1.273         1.267         1.00         1.273         1.267         1.00         1.273         1.267         1.00         1.273         1.267         1.00         1.273         1.267         1.00         1.271         1.267         1.00         1.271         1.267         1.00         1.271         1.267         1.00         1.271         1.267         1.01		SCFM	066																																						
S/It         0.52         0.70         0.73         1.00         0.52         0.70         0.73         1.00         0.52         0.70         0.73         1.00           AMPS         655         6.66         6.14         6.80         7.84         7.34         130         313         314         313         314         313         314         313         314         313         314         315		MBh†	43.10	39.20			-			32.45																															
AMPS*         6.55         6.66         6.74         6.80         7.88         7.94         7.88         7.94         7.88         7.94         7.88         7.94         7.93         1.65         7.66         7.7         2.67         2.88         7.94         7.93         7.67         7.93         7.67         7.89         7.93         7.67         7.05         7.17         7.94         1.050         7.73         7.67         7.93          7.93         7.93         <	Comtort	S/T‡	0.52	0.70	0.73	1.00	0.52	0.70	0.73	1.00	0.52																														
HIP         239         236         234         233         271         269         316         311         309         325         355         357         357         157         135         127         350         351         357         357         357         357         357         357         357         357         357         357         357         357         357         357         356         35.5         35.5         35.5         35.7         35.8         35.8         35.8         35.8         35.8         35.8         35.8         35.8         37.7         29.8         37.7         29.8         37.4         37.4         37.7         20.7         0.77         0.77         0.76         0.81           MIP         358         6.77         0.74         0.76         0.76         0.77         0.79         100         0.57         0.76         0.81           MIP         358         6.88         6.98         8.19         8.10         8.15         8.19         8.10         8.10         8.10         8.10         8.10         8.10         8.10         8.10         8.10         8.10         1.1050         1.1050         1.1050         1.1050	+ De-Humidifv	AMPS*	6.55	6.66	6.74	6.80	7.88	7.94	7.98	8.00	9.35																														
LOPR         158         144         134         127         158         144         134         127         158         145         159         155         157         153         124         159         157         150         150         150           SCFM         1050         SCFM         1050         SCFM         1050 <th< th=""><th></th><th>HI PR</th><th>239</th><th>236</th><th>234</th><th>233</th><th>276</th><th>273</th><th>271</th><th>269</th><th>318</th><th>314</th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th></th<>		HI PR	239	236	234	233	276	273	271	269	318	314																													
SFFM         1050 <t< th=""><th></th><th>LO PR</th><th>158</th><th>144</th><th>134</th><th>126</th><th>158</th><th>144</th><th>134</th><th>127</th><th>158</th><th>144</th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th></t<>		LO PR	158	144	134	126	158	144	134	127	158	144																													
MBht         43.46         39.55         36.75         34.96         41.32         37.59         34.94         39.14         37.56         37.10         37.56         37.56         37.56         37.57         24.96         37.71         29.48         28.36         37.56         37.56         37.50         37.56         37.50         37.56         37.57         37.66         37.7         37.97         37.00         37.51         37.4         37.17         39.48         39.36         37.56         37.57         37.7         409         405         47.7         37.7         39.7         409         405         47.7         37.66         37.7         37.7         409         405         47.7         37.9         47.7           AMPS*         239         236         37.7         37.1         36.7         37.7         36.7         37.7         40.9         405         40.7         47.9         47.7           AMPS*         239         236.7         37.1         31.7         35.7         35.7         40.9         405         40.7         40.7         40.7         40.7         40.7         40.7         40.7         40.7         40.7         40.7         40.7         40.7		SCFM	1050				1050				1050			-	020			105	0			1050																			
S/T         0.53         0.71         0.74         1.00         0.55         0.76         0.78         1.00         0.57         0.76         0.81           AMPS*         6.68         6.79         6.88         6.93         8.09         8.15         8.19         8.11         8.13         1.21         11.31         13.11         13.10         15.18         13.33         14.94           AMPS*         6.68         6.79         6.88         6.93         8.09         8.15         8.19         8.11         351         357         357         409         405         403         457         454         439         457           MPR         239         236         237         321         311         365         361         357         357         409         405         403         453         453         453           LOPR         160         146         137         163         132         131         165         153         143         153         143         153         143         153         153         153         153         153         153         153         153         153         153         153         153         153		MBh†	43.48	39.55		34.96				33.49													31.43	27.56	27.36																
AMPS*         6.68         6.79         6.88         6.33         8.09         8.15         8.19         8.11         235         36.7         35.7         35.7         409         405         464         399         457           HPR         239         236         237         277         274         271         270         319         315         311         365         361         357         357         409         405         403         402         464         399         457           LOPR         160         146         135         120         313         163         143         165         152         141         139         163         152         143           CFPM         1080         35.7         35.1         143         153         31.7         31.4         155         143         150         153         163         152         143           ASTM         39.40         36.72         35.16         41.63         35.73         35.74         31.71         31.83         31.71         34.80         35.71         27.66           MBH         43.11         39.40         6.52         1.00         0.56         0.79 <th>Efficiency</th> <th>S/T‡</th> <th>0.53</th> <th>0.71</th> <th>0.74</th> <th>1.00</th> <th>0.53</th> <th>0.72</th> <th>0.75</th> <th>1.00</th> <th>0.54</th> <th></th> <th>0.57</th> <th>0.76</th> <th>0.81</th> <th>1.00</th>	Efficiency	S/T‡	0.53	0.71	0.74	1.00	0.53	0.72	0.75	1.00	0.54											0.57	0.76	0.81	1.00																
HIPR         239         236         234         233         277         274         271         270         319         315         311         365         361         357         357         409         405         403         402         464         399         457           LO PR         160         146         135         129         161         147         137         131         165         151         140         137         166         152         141         139         163         152         143           SCFM         1080         1200         1200         1200         1200         1200         1200         1200         1200         1200         1200         166         152         141         139         165         157         166         152         143         150	Elliciency	AMPS*	6.68	6.79	6.88	6.93	8.09	8.15	8.19	8.21	9.61												13.38	14.94	14.94																
LO PR         160         146         135         129         161         147         137         131         163         149         137         166         152         141         139         168         152         143           SCFM         1080         1200         166         152         141         133         140         131         1200         166         152         130         160         163		HI PR	239	236	234	233	277	274	271	270	319	315						_				464	399	457	456																
SCFM         1080         1200         1200         1200         1200         1050         29.71         27.60         29.71         27.66         29.71         27.66         29.71         27.66         29.71         27.66         29.71         27.66         29.71         27.66         29.75         0.72         0.75         0.70         0.55         0.77         0.79         1.00         0.57         0.78         0.81         27.60         29.71         27.60         29.71         27.66         29.71         27.66         29.76         29.76         29.76         29.76         29.71         27.66         29.71         27.66         29.76         29.76         13.31         13.30         13.01         15.06         14.90         13.76         13.03         13.01         15.06         29.71         27.86         29.76         29.71         27.86         29.76         29.71         27.86         29.76         29.71         27.96		LO PR	160	146	135	129	161	147	137	131	163	149									139	168	152	143	143																
MBht         43.11         39.40         36.72         35.16         41.64         38.08         35.51         34.83         39.55         36.14         33.70         33.29         37.40         34.16         31.73         29.54         29.02         32.60         29.71         27.66           S/T‡         0.53         0.72         0.75         1.00         0.56         0.77         0.79         1.00         0.57         0.79         0.82         0.81           AMPS*         6.49         6.62         6.70         0.79         1.00         0.57         0.79         0.82         1.30         13.01         15.00         0.57         0.78         0.81           AMPS*         6.49         6.62         6.70         8.10         8.76         9.76         9.75         11.39         11.40         11.39         13.01         15.08         14.90         14.90           AMPS*         232         230         229         275         269         269         317         314         312         364         361         363         14.90         14.90           AMPS*         235         230         229         272         269         367         312 <t< th=""><th></th><th>SCFM</th><th>1080</th><th></th><th></th><th></th><th>1200</th><th></th><th></th><th></th><th>1200</th><th></th><th>ĺ</th><th>F</th><th>200</th><th></th><th>Í</th><th>105</th><th>0</th><th></th><th></th><th>1050</th><th></th><th></th><th></th></t<>		SCFM	1080				1200				1200		ĺ	F	200		Í	105	0			1050																			
S/T‡         0.53         0.72         0.75         1.00         0.56         0.77         0.79         1.00         0.57         0.78         0.81           AMPS*         6.49         6.62         6.70         6.74         8.11         8.20         8.26         9.76         9.75         1.39         11.39         13.07         13.03         13.01         15.08         14.38         14.30           AMPS*         6.49         6.62         6.70         8.71         8.26         9.68         9.74         9.76         9.75         11.39         11.39         13.07         13.03         13.01         15.08         14.38         14.30           AMPS*         6.49         6.62         6.77         272         269         269         317         314         312         364         361         359         359         403         403         464         460         459           LO PR         161         147         136         151         140         138         164         154         143         166         152         161         154         143         166         152         161         154         143         168         154         143 <th></th> <th>MBh†</th> <th>43.11</th> <th>39.40</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th>34.83</th> <th></th> <th>29.71</th> <th>27.66</th> <th>27.43</th>		MBh†	43.11	39.40						34.83													29.71	27.66	27.43																
AMPS*         6.49         6.62         6.74         8.11         8.20         8.26         9.68         9.74         9.75         11.39         11.40         13.07         13.07         13.01         15.08         14.90         14.90           HIPR         235         232         230         229         272         269         269         317         314         312         312         364         361         359         408         405         403         464         460         459           LO PR         161         147         136         151         140         152         143         168         154         143         166         152         161         154         143         166         152         161         154         143         168         154         143		S/T‡	0.53	0.72	0.75	1.00	0.56	0.76	0.79	1.00	0.56											0.57	0.78	0.81	1.00																
235     232     230     229     275     269     317     314     312     364     361     359     368     408     405     403     403     464     460     459       161     147     136     131     165     151     140     138     167     152     142     140     168     154     143     166     152     141     139     168     154     143	Maximum	AMPS*	6.49	6.62	6.70	6.74	8.11	8.20	8.26	8.26	9.68											15.08	14.98	14.90	14.88																
161 147 136 131 165 151 140 138 167 152 142 140 168 154 143 143 166 152 141 139 168 154 143		HI PR	235	232	230	229	275	272	269	269	317	314										464	460	459	458																
		LO PR	161	147	136	131	165	151	140	138	167	152		_							139	168	154	143	142																

								010	0110	211 C	W YOU	с 1 4+	ANAV6	***0	00+0	018 Size Outdoor With EOMAV60***  Stace E hadoor Occilia	1000		ζ					
								2	240		Outdoor Ambient Temperature - Degrees F, Dry Bulb	mbient T	emperati	ure - De	grees F, I	Jry Bulb	000		R					
			9	65			[	75			85				95		L		105			-	115#	
										Γ	Entering Indoor Temperature – Degrees F, Wet Bulb	ndoor Te	mperatu	re - Deg	rees F, V	fet Bulb								
STAGE-5 Mode	5 Mode	72	29	63††	21	72	67	63††	57	72	67 6	63††	57 7	72 (	67 63††	11 57	72	67	63††	57	72	67	63††	57
	SCFM		1227	27			-	330			Z.				1184				1110					
	MBh†	58.25	53.26	49.62	-			-	45.10	52.90			42.24 49	49.62 45	45.38 42.27		-		39.38	36.80				
Comfort	S/T‡	0.51	0.67	0.70	1.00	0.52	0.70	0.72	1.00	0.52	0.69 (	0.72 1	1.00 0.	0.52 0	0.69 0.	0.72 1.00	0 0.52	2 0.69	0.71	1.00				
+ Do Unmidifie	AMPS*	12.59	10.61	16.67	18.98	14.52	12.64	19.00	8.86	16.32	14.79 8	8.87 1	10.76 18	18.53 16	16.81 10	10.77 12.63	3 8.60	0 19.23	3 12.64	14.62				
	HI PR	340	306	443	502	390	352	503	256	435	403	256 2	298 4	495 4	448 29	298 344	4 263	508	344	393				
	LO PR	126	161	148	150	129	163	150	132	126	165	132 1	137 1	129 1	163 1:	136 138	3 157	165	138	140				
	SCFM		4	1400			1	400			1400		╞		1400		_		1400			ſ	1400	
	MBh†	59.48	54.45	50.78	47.82	56.66	51.86	48.37	45.84	53.76	49.21 4	45.91 4:	43.81 50	50.77 46	46.50 43.37	.37 41.72	2 47.74	4 43.71	40.79	39.59	44.60	40.84	38.13	37.36
	S/T‡	0.52	0.70	0.72	1.00	0.53	0.71	0.73	1.00	0.53	0.72 (	0.74 1	1.00 0.	0.54 0	0.73 0.	0.75 1.00	0 0.55	5 0.74	0.77	1.00	0.56	0.76	0.79	1.00
Efficiency	AMPS*	8.60	8.76	8.87	8.92	10.61	10.71	10.77	10.77	12.64	12.64 1	12.64 1	12.62 14	14.79 14	14.71 14	14.63 14.60	0 16.81	1 16.66	3 16.52	16.45	19.23	18.98	18.78	18.71
	HI PR	263	259	256	254	306	302	298	297	352	347	344 3	342 4	403 3	397 30	393 392	2 448	3 442	439	437	508	502	499	497
	LO PR	157	143	132	125	161	147	136	132	163	148	138 1	135 1	165 1	150 1	139 137	7 163	148	137	134	165	150	139	137
	SCFM		14	1440			Ĩ	600			1600				1600				1400			ľ	1400	
	MBh†	59.00	54.13	50.59	47.97	56.77	52.12	48.76	47.31	53.76	49.38 4	46.21 4	45.16 50	50.67 46	46.57 43	43.60 42.93	3 47.05	5 43.21	40.42	39.32	43.91	40.34	37.77	37.08
	S/T‡	0.53	0.71	0.73	1.00	0.55	0.74	0.77	1.00	0.55	0.76 (	0.78 1	1.00	0.56 0	0.77 0.	0.79 1.00	0 0.55	5 0.75	0.77	1.00	0.56	0.77	0.79	1.00
Maximum	AMPS*	8.60	8.76	8.87	8.92	10.61			10.77	12.64			<b>.</b>	-			-			ľ	-	18.98	18.78	18.71
	HI PR	263	259	256	254	306			297	352			_				-				-	502	499	497
	LO PR	157	143	132	125	161	147	136	132	163	148	138	135 1	165 1	150 1	139 137	7 163	148	137	134	165	150	139	137
						Ċ	¢		11.11			00//			10 1 11					C				Ī
					อ้	49 SI		itdoo		EN (2	949 Size Outdoor With EN(A,D,W)4X60L24**+*8MV*1352422**L	)4X60	L24**	W8*+	V*135	2422		Stage 5 Indoor Cooling	Indoc	sr Co	oling			
						ļ				5	Outdoor Ambient Temperature – Degrees F, Dry Bulb	mbient T	emperat	ure – De	grees F, .	Ory Bulb								
			9	65			-	75			85				95				105			-	115#	
											ring	ndoor Te	emperatu	re - Deg	rees F, V	/et Bulb								
STAGE-5 Mode	5 Mode	72	67	63††	57	72	67	63††	57	72	67 6	63††	57 7	72 (	67 63††	811 57	72	67	63††	57	72	67	63††	57
	SCFM		12	1236			-	200			1196		_		1184				1110					
	MBh†	54.08	49.07	45.47	42.65			44.02	41.42	50.72		42.67 4	40.47 48	48.93 44	44.41 41	41.17 39.33	-	9 42.29	39.20	37.41				
Comfort	S/T‡	0.52	0.69						1.00	0.52														
+	AMPS*	10.98	10.75			12.30	12.06		11.78	13.91	13.65 1				15.44 15	15.25 15.15	5 17.61	1 17.32	2 17.13	17.03				
De-Humidify	HI PR	236	233	232	231	273		268	267	315	311				356 3!	353 352	2 410	405	402	401				
	LO PR	151	137	128	120	152	139	129	122	154	140	130 1	124 1	156 1	142 1:	132 127	7 156	143	133	127				
	SCFM		12	1200			Ŧ	200			1200				1200				1200				1200	
	MBh†	53.80	48.81	48.81 45.22	42.21			44.02	41.42	50.75	46.06 4	_	40.51 49	49.03 44	44.50 41.26	.26 39.51	•	2 42.79	39.67	38.37	45.05	40.90	37.94	37.10
Efficiency	S/T‡	0.51	0.68		1.00				1.00	0.52											0.55	0.75	0.77	1.00
Elliciency	AMPS*	10.89	10.66		10.39	·		-	11.78	13.92	9	_	~	0	_	C	0 17.83		-		20.20	19.89	19.67	19.63
	HI PR	236	233	232	231	273	270	268	267	315	311	309	308 3	360 3	356 31	354 352	2 411	406	403	402	466	461	458	457
	LO PR	150	137	127	119	152	139	129	122	154	141	131 1	124 1	156 1	143 1;	132 127	7 158	145	135	131	161	147	137	134
	SCFM		14	1400		-	-	a a			1400		-		1400		-		1400			ľ	1200	
	MBh†	54.94	49.92	49.92 46.30	44.40	53.44	48.55	45.04	43.51	51.76	47.05 4	43.64 4	42.52 49	49.94 45	45.40 42.12	:12 41.40	0 47.94	4 43.60	) 40.47	40.16	45.01	40.92	37.97	37.11
Movimum	S/T‡	0.53	0.71			-			1.00	0.54	0.74 (			0.55 0		0.78 1.00			0.80	1.00	0.55	0.75	0.77	1.00
	AMPS*	11.36	11.12			·	-	12.37	12.30	14.45	14.19 1	13.99 1:	13.94 16	16.30 16	16.03 15	15.84 15.80	80 18.41	1 18.12	2 17.92	17.91	20.18	19.90	19.70	19.64
		234	232	230	229	273		268	266	315									405	404	466	462	458	457
	LU PR	104	141	2	071	001	143	33	R7.1	801	C <del>1</del>	134	132	00	14/	130 135	201 0	149	138	38	101	147	137	134

Outloor Ambient Temperature - Degrees F, Dry Bull         Control         Control<									960	Size (	Jutdo	or ⊗	'ith F(	CM4X	(60***	'L Sta	960 Size Outdoor With FCM4X60***L Stage 5 Indoor Cooling	οορι	r Coo	ling					
65         75         75         66         75												utdoor A	Ambient	Tempera	iture - D	egrees F,	Dry Bulb								
Elementer el negrese F, Me Builb         i dit i 57         i dit i 56         i dit i 57         i dit i 57         i dit i 56         i dit i 57         i dit i 77         i dit i 67         i dit i 67         i dit i 67         i dit i 77         i dit 77         i dit i 77 <th col<="" th=""><th></th><th></th><th></th><th></th><th>25</th><th></th><th></th><th></th><th>5</th><th></th><th></th><th>85</th><th></th><th></th><th></th><th>95</th><th></th><th></th><th></th><th>105</th><th></th><th></th><th>115#</th><th></th></th>	<th></th> <th></th> <th></th> <th></th> <th>25</th> <th></th> <th></th> <th></th> <th>5</th> <th></th> <th></th> <th>85</th> <th></th> <th></th> <th></th> <th>95</th> <th></th> <th></th> <th></th> <th>105</th> <th></th> <th></th> <th>115#</th> <th></th>					25				5			85				95				105			115#	
E-5 Mode         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         6311         57         72         67         631         57         72         67         631         57         57         57         57         57         57         57         57         57         57         57         57         57         57         57         57         57         57         57         55         57         55         56         57         55         56         57         55         56         57         55         57         55         56         57         55         57         55         57         55         57         55         57         55         57         55         57         55         57         55         57         55         57         55         57         55         57         55         57         55         57         56         57         57         5												Entering	Indoor 1	emperat	ure – D€	egrees F,	Wet Bulb								
X + 148         156         1514         161         161         163         156         156         156         156         156         156         156         156         150         1	STAGE	-5 Mode	72	67	63††	57	72	67	63††	57	72		63††	57	72			_	_				63††	57	
WBH         71:59         65:29         60.75         55:91         68.97         6.2.30         61.47         56.15         5.3.61         58.90         6.7.71         1.00         0.52         0.69         0.771         1.00         0.52         0.69         0.771         1.00         0.52         0.69         0.771         1.00         0.52         0.69         0.771         1.00         0.52         0.69         0.771         1.00         0.52         0.69         0.771         1.00         0.52         0.69         0.771         1.00         0.52         0.69         0.771         1.00         0.52         0.69         0.771         1.00         0.52         0.69         0.771         1.00         0.52         0.69         0.771         0.00         0.52         0.69         0.771         0.00         0.52         0.69         0.771         0.00         0.52         0.69         0.771         0.00         0.52         0.69         0.771         0.00         0.52         0.69         0.771         0.00         0.52         0.69         0.771         0.00         0.52         0.69         0.771         0.00         0.52         0.69         0.771 <th0.01< th=""> <th0.71< th="">         0.60</th0.71<></th0.01<>		SCFM		14	881			15	99			151	4			1440				1367					
Sf1         0.51         0.67         0.70         1.00         0.52         0.69         0.71         1.00         0.52         0.69         0.71         1.00         0.52         0.69         0.71         1.00         0.52         0.69         0.71         1.00         0.52         0.69         0.71         1.00         0.52         0.69         0.71         1.00         0.52         0.69         0.71         1.00         0.52         0.69         0.71         1.00         0.52         0.69         0.71         1.00         0.52         0.69         0.71         1.00         0.52         0.69         0.71         1.00         0.52         0.69         0.71         1.00         0.52         0.69         0.71         0.77         1.268         1.269         1.269         1.269         1.269         1.269         1.269         1.269         1.269         1.269         1.269         1.260         1.261         1.460		MBh†	71.59	65.29			68.97	62.96	58.62	54.72								1			06				
AMPS*         12.59         10.61         16.87         18.39         14.32         14.32         14.32         14.32         14.32         14.33         15.3         15.4         14.52         34.3         333         3	Comfort	S/T‡	0.51	0.67	0.70	1.00	0.52	0.69	0.71	1.00	0.52										0				
HIP         340         306         433         502         390         352         503         256         435         436         436         344         383         333           LOPR         126         161         148         150         129         163         132         126         157         166         138         140          1600           SCFM         126         161         148         150         132         150         153         157         166         138         140          1600           Mbh         72.44         6610         61.25         51.74         601         55.99         52.83         67.1         0.74         1.00         0.54         0.74         0.76           Mbh         72.44         6610         61.25         51.74         601         55.99         52.93         52.94         57.00         53.13         50.74         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.76         0.74         0.76         0.74         0.76         0.76         0.74         0.76         0.7	+ De-Humidify	AMPS*	12.59	10.61	16.67	18.98	-	12.64	19.00	8.86									-		32				
		HI PR	340	306	443	502	390	352	503	256	435	403	256	298	495						33				
SCFM         1600         1610         17.1         17.1         17.1         17.1         17.1         12.64         1		LO PR	126	161	148	150	129	163	150	132	126	165	132	137	129						0				
MBH         72.44         66.10         61.52         57.24         69.15         63.13         58.15         65.06         65.82         60.10         55.95         53.13         50.51         58.86         53.83         50.16         47.11           S/T         0.51         0.68         0.71         100         0.52         0.70         0.73         1.00         0.53         0.71         0.74         1.00         0.54         0.74         0.70           AMPS*         8.60         8.76         8.87         8.92         1061         10.77         10.77         12.64         12.64         12.64         12.64         12.64         12.64         12.64         12.67         14.60         16.81         16.66         16.52         16.45         13.7         13         18.92         18.96         50.74         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.77         0.86		SCFM		16	00			16	00			160	0			1600				1600			1600		
S/T         0.51         0.68         0.71         1.00         0.52         0.70         0.73         1.00         0.53         0.71         0.74         1.00         0.54         0.74         0.76         0.77         0.70         0.73         0.71         0.71         1.00         0.55         0.74         0.76         0.76         0.74         0.76         0.74         0.76         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.74         0.76         0.76         0.74         0.76		MBh†	72.44	66.10			-		58.78	55.06				-							1			45.62	
AMPS*         8.60         8.76         8.87         8.92         10.61         10.77         10.77         12.64         12.64         12.62         14.75         14.66         16.52         16.45         19.23         18.98         18.78           HIPR         263         259         256         254         306         302         298         297         352         347         344         342         403         397         393         392         448         442         439         437         508         502         499           LOPR         157         143         132         126         132         163         148         137         134         165         150         139           SCFM         To:23         66.23         61.81         66.70         61.24         57.27         56.00         63.17         58.03         54.29         53.85         50.35         48.26         55.04         50.77         1600           SCFM         To:223         66.23         61.30         0.55         0.78         0.78         0.78         0.78         0.78         0.77         0.80         160         65.04         50.76         0.77         0.80	766 - 1	S/T‡	0.51	0.68	0.71	1.00	0.52	0.69	0.72	1.00	0.52													1.00	
HIP         263         259         254         306         302         347         344         342         403         397         393         392         448         442         439         508         502         499           LOPR         157         143         132         125         161         147         136         132         148         138         135         165         150         139         137         148         137         149         165         150         139           SCFM         Isto         I	ETTICIENCY	AMPS*	8.60	8.76		8.92	10.61	10.71	10.77	10.77														18.71	
LOPR         157         143         132         125         161         147         136         132         148         137         148         137         134         165         150         139           SCFM         160         160         130         137         143         137         143         165         150         139           SCFM         1600         160         1305         100         2000         2000         2000         163         148         137         148         150         160           NBht         72.23         66.23         61.81         58.05         53.16         58.65         53.88         50.35         48.26         55.04         50.77         47.31           MBht         72.23         66.23         61.81         50.76         0.77         0.80         0.54         0.77         0.80         0.55         48.26         55.04         50.74         0.76           MBht         72.23         66.39         63.97         57.77         66.70         61.26         1.77         0.80         1.76         0.72         0.77         0.76         0.77         0.76         0.77         0.76         0.77         0		HI PR	263	259	256	254	306	302	298	297	352	347	344	342	403									497	
SCFM         1600         1905         2000         2000         1610         1610         1610 <th< th=""><th></th><th>LO PR</th><th>157</th><th>143</th><th>132</th><th>125</th><th>161</th><th>147</th><th>136</th><th>132</th><th>163</th><th>148</th><th>138</th><th>135</th><th>165</th><th></th><th></th><th></th><th></th><th></th><th></th><th>Ċ</th><th></th><th>137</th></th<>		LO PR	157	143	132	125	161	147	136	132	163	148	138	135	165							Ċ		137	
MBht         72.23         66.23         61.81         58.03         59.1         57.77         66.70         61.24         57.27         56.00         63.17         58.03         54.29         53.46         58.65         53.88         50.35         48.26         55.04         50.57         47.31           SfT         0.52         0.69         0.72         1.00         0.54         0.75         0.76         0.77         0.66         0.77         0.69         0.72         0.76         1.00         0.56         0.77         0.80         1.00         0.54         0.74         0.74         0.76           AMPS*         8.60         8.76         8.77         18.04         12.65         12.64         12.64         12.64         12.64         12.64         12.64         12.62         14.77         14.60         16.81         16.66         16.52         16.45         19.23         18.98         18.78           AMPS*         8.60         8.76         256         377         347         342         4.03         397         393         397         393         397         488         442         439         786         50.26         499           AMPS*         269 <th></th> <th>SCFM</th> <th></th> <th>16</th> <th>80</th> <th></th> <th></th> <th>19</th> <th>05</th> <th></th> <th>ĺ</th> <th>200</th> <th>0</th> <th></th> <th></th> <th>2000</th> <th></th> <th></th> <th>Í</th> <th>1600</th> <th></th> <th></th> <th>1600</th> <th></th>		SCFM		16	80			19	05		ĺ	200	0			2000			Í	1600			1600		
S/T‡     0.52     0.69     0.72     1.00     0.54     0.76     1.00     0.56     0.77     0.80     1.00     0.54     0.74     0.76       AMPS*     8.60     8.76     8.87     8.97     10.61     10.71     10.77     12.64     12.64     12.62     14.79     14.60     16.81     16.66     16.52     16.45     19.23     18.96     18.78     1       AMPS*     8.60     8.76     8.78     12.64     12.64     12.62     14.79     14.60     16.81     16.66     16.52     16.45     19.23     18.96     18.78     1       HIPR     263     259     254     306     302     298     297     352     347     344     343     397     393     397     393     392     448     422     439     508     502     499       HIPR     263     157     143     136     132     148     138     137     148     137     134     165     150     150     150     150     150     150     150     150     150     150     150     150     150     150     154     153     149     137     151     150     150     150     139<		MBh†	72.23	66.23		58.03		64.18	59.97															45.78	
AMPS*         8.60         8.77         8.92         10.77         10.77         12.64         12.64         12.62         14.77         14.60         16.81         16.66         16.52         16.45         19.23         18.98         18.78           HIPR         263         259         254         306         302         298         297         352         347         344         342         403         397         393         392         448         442         437         508         502         499           LOPR         157         143         132         163         148         137         163         150         150         139         137         163         150         139		S/T‡	0.52	0.69	0.72	1.00	0.54	0.73	0.76	1.00	0.55		0.78											1.00	
263         259         256         254         306         302         307         303         397         393         397         393         392         448         442         437         508         502         499           157         143         132         161         147         136         132         148         138         135         165         150         139         137         163         148         150         139	Maximum	AMPS*	8.60	8.76	8.87	8.92	10.61	10.71	10.77	10.77	12.64			-				-						18.71	
157         143         132         161         132         163         148         138         135         165         150         139         137         163         164         150         139		HI PR	263	259	256	254	306	302	298	297	352	347	344	342	403			-						497	
		LO PR	157	143	132	125	161	147	136	132	163	148	138	135	165							Ċ		137	

† Total capacities are net (I.D blower heat subtracted) system capacities based on 25' line set.

If additional tubing length and/or indoor unit is located above outdoor unit, a slight variation in capacity may occur.

\* System amps are total of indoor and outdoor amps

S/T are based on 80 F db entering air at the indoor coil. For sensible capacities at other than 80 F db, deduct 835 Btuh per 1000 cfm of indoor ++

coil air from MBhxS/T for each degree below 80 F, or add 835 Btuh per 1000 cfm of indoor coil air from MBhxS/T for each degree above 80 F

11 At TVA rating indoor condition (75 F db/ 63 F wb), All other indoor air temperatures are at 80 F db # System runs Stage 5 Efficiency Mode for Comfort+dh Mode at 115 degrees F outdoor temperature.

421 01 5900 00

# **R-410A QUICK REFERENCE GUIDE**

- R-410A refrigerant operates at 50% 70% higher pressures than R-22. Be sure that servicing equipment and replacement components are designed to operate with R-410A.
- R-410A refrigerant cylinders are rose colored.
- Recovery cylinder service pressure rating must be 400 psig, DOT 4BA400 or DOT BW400.
- R-410A systems should be charged with liquid refrigerant. Use a commercial type metering device in the manifold hose.
- Manifold sets should be 750 psig high-side and 200 psig low-side with 520 psig low-side retard.
- Use hoses with 750 psig service pressure rating.
- Leak detectors should be designed to detect HFC refrigerant.
- R-410A, as with other HFC refrigerants, is only compatible with POE oils.
- Vacuum pumps will not remove moisture from oil.
- Do not use liquid line filter-driers with rated working pressures less than 600 psig.
- Do not install a suction line filter-drier in liquid line.
- POE oils absorb moisture rapidly. Do not expose oil to atmosphere.
- · POE oils may cause damage to certain plastics and roofing materials.
- Wrap all filter-driers and service valves with wet cloth when brazing.
- A liquid line filter-drier is required on every unit.
- Do not use with an R-22 TXV.
- If indoor unit is equipped with an R-22 TXV, it must be changed to an R-410A TXV.
- Never open system to atmosphere while it is under a vacuum.
- When system must be opened for service, break vacuum with dry nitrogen and replace all filter-driers.
- Do not vent R-410A into the atmosphere.
- Do not use capillary tube indoor coils.
- Observe all WARNINGS, CAUTIONS, NOTES, and bold text.

#### AHRI CERTIFIED.

Use of the AHRI Certified TM Mark indicates a manufacturer's participation in the program For verification of certification for individual products, go to www.ahridirectory.org.

